# urban ambiance

PART	DESCR	IPTION	QUANTITY		
А	Fixture		1		
В	Glass sl		1		
С	Round r	nut	3		
HAI	RDWAF	RE CONTE	NTS (not actual	A B () Size)	
	F	~	NTS (not actual		
(		BB	CC		
(					
			Round Mounting Pl	te Hex nut	Knurle
	icrew #8-32)	Wire nut		(#8-32)	(



#### **Questions?**

Call our Customer Care Team at 1-855-303-4229

urban ambiance www.urbanambiance.com

## Safety Information

Please read and understand this entire manual before attempting to assemble, operate or install the product.

CAUTION: Read instructions carefully and turn electricity off at main circuit breaker panel before beginning installation.

CAUTION: Risk of fire. Min. 90°C supply conductors. Consult a qualified electrician to ensure correct branch circuit conductor.

WARNING: If any Special Control Devices are used with this fixture, follow instructions carefully to assure full compliance with N.E.C. requirements. If there are any questions, contact a qualified electrical contractor.

CAUTION: All glass is fragile. Use care when handling glass shades and bulbs.

### Preparation

1. Before beginning installation, make sure all parts are included using the contents diagrams from page 1. If any part is missing or damaged, do not attempt to assemble, install or operate the product.

- 2. Estimated assembly time: 30 minutes.
- 3. Tools required for assembly (not included): Phillips screwdriver, pliers, wire stripper, safety glasses, electrical tape, ladder.

### Care and Maintenance

Shut off main power supply before cleaning product or changing light bulbs. To clean, wipe with damp cloth. Do not use abrasive cleaners or cleaners that contain alcohol.

## Assembly Instructions

	1. Screw screw (AA) onto round mour hex nut (DD) to secure it tight.	ting plate (CC) and us	se		
	Hardware Used				
	AA Screw		X2		
	CC Round Mounting Plate		X1		
	DD Hex nut		X2		
$\frac{2}{2}$	2. Attach assembled parts from Step mounting screws supplied with the ou (not included).		g the		

## **Assembly Instructions** 3. Strip 3/8" of insulation from the electrical wire ends. Using 3 wire nuts (BB), connect white fixture wire to the white supply wire from the outlet box; connect the black fixture wire to the black supply wire. Connect the fixture ground wire and supply ground wire using a wire nut or by fastening to the ground screw on the round mounting plate. Push all wire connections into the outlet box. (BB) 🖻 (BB) BB Wire nut **{ }** Х3 4. Attach fixture (A) to screws (AA) using knurled ball nut (EE). 4 Secure tightly. (EE Knurled ball nut X2 5. Screw lamp (not included) into fixture socket. 5 Use 60-watt MAX incandescent medium base lamp, SBCFL or SBLED. С Attach glass shade (B) to fixture (A) and use round nut (C) to secure tightly. А ∯€ В



Urban ambiance www.urbanambiance.com