

# 5800RP

## WIRELESS REPEATER



Honeywell's 5800RP is a wireless repeater that extends the range of 5800 Series RF devices. For installations that require increased RF range, the 5800RP eliminates the need to run wires to a remotely installed secondary receiver and also eliminates the need to upgrade to a larger control panel that supports two receivers.

### FEATURES:

- Extends the range of 5800 Series wireless devices
- Receives alarm, status and control messages from 5800 RF devices, and repeats these messages to the control panel via the primary receiver
- Compatible with all 5800 Series wireless devices (including bidirectional devices)
- UL residential burglary listed when used with optional transformer (300-07753) or consist-of-kit 5800RP-ULKT (5800RP + 300-07753)
- AC powered with a six-hour battery back-up
- Tamper protected

### SPECIFICATIONS:

#### Dimensions:

- 7-3/8" W x 4-3/8" (10-7/8" with antenna) H x 2-1/8" D/188mm W x 112mm H (277mm with antenna) x 54mm D

#### Input Voltage:

- 9VAC, 15VA (transformer sold separately - 300-07753)

#### Current:

- 80mA

#### Battery Pack:

- Rechargeable, part number 300-03865

#### Compatibility:

- Compatible with the 5881ENL, M & H family, 6150RF, 6160RF, 53883H for VISTA™ systems and all LYNX systems

## ORDERING

#### Part Numbers

5800RP  
300-07753  
5800RP-ULKT  
300-03865

#### Description

Wireless Repeater  
Transformer for UL Installs, 9VAC, 15VA  
5800RP with 300-07753 Transformer  
Replacement Rechargeable Battery

#### For more information:

[www.honeywell.com/security](http://www.honeywell.com/security)

#### Automation and Control Solutions

Honeywell Security and Fire  
2 Corporate Center Dr. Suite 100  
P.O. Box 9040  
Melville, NY 11747  
1.800.467.5875  
[www.honeywell.com](http://www.honeywell.com)

**Honeywell**