



💰 App Store

Soogle play

Sensibo Sky User Manual



App Installation Wizard

Installation A/C settings Scheduling Geofencing and Anticipate my Arrival feature **Open API and integrations** Sharing your AC with others FAQ and Troubleshooting How can I turn the A/C on or off? How can I change the A/C state to cool, heat, etc.? How can I change the fan level of my A/C? How can I set a timer for my A/C? How can I change the name or icon of mv A/C? How can I invite other people to use mv A/C? How can I set and edit schedules for my A/Cs? How can I delete a schedule? How can I setup another Smart A/C? How can I reset my Sensibo user password? I get a "device is disconnected" notification in the app, what does it mean? Cannot join Wi-Fi network Android only - Network has no internet connection Android only - App cannot find your smart A/C's network Android only - Cannot connect to your Smart A/C network Smart A/C Installation issues

My Smart A/C cannot connect to my local network Cannot join Wi-Fi network

Network has no internet connection

Certification



Welcome

Hi,

In this manual we will guide you through the installation and operation of Sensibo Sky: Make your air conditioner smart.

Sensibo Sky is a device that upgrades your existing air conditioner to connect to the internet and makes it smart. It lets you control the air conditioner from anywhere using your smartphone, monitor the temperature and humidity remotely, set 7-day scheduling, make your air conditioner turn on and off automatically and much more.

Compatibility

Sensibo can be installed to control any air conditioner that comes with a remote control. These include split (wall mounted) air conditioners, central air conditioners with a remote control, window air conditioners, room air conditioners, cassettes and more. As long as the air conditioner can be controlled with a remote, Sensibo can be installed and used with it.

Sensibo also needs WiFi access to operate.



Installation

App Installation Wizard

Sensibo app will guide you through the installation process.

Download the free Sensibo app to your mobile device:

For iOS devices, search for 'Sensibo' on the app store or go to <u>sensibo.com/pages/ios</u>

For Android devices, search for 'Sensibo' on Google Play store or go to <u>sensibo.com/pages/android</u>



Installation

1. Launch the app and sign up. If you already signed, just log in:

🔻 🖌 🔒 12:30	▼ 📶 🖬 12:30				
	< Sign up				
SENSIBO Your smart air conditioner has arrived.	Email Address First Name Last Name Password Verify password				
	SIGN UP				
Let's get you started.					
SIGN UP LOG IN					
Dont have a Sensibo kit yet? <u>Get yours here</u>					



2. If this is your first installation, select 'Sensibo Sky' from the menu.

If you already have some devices install, click on the 'settings' icon and select 'Setup a new Sensibo device'





3. Scan the QR code that is provided on the device





4. Select a name and icon for the AC and your Sensibo Inside

No SIM ᅙ	11:00	1 21% 🗔	No SIM 중	5:46 PM
	Smart A/C Setup	? :		and name for this A/C. er defined data will be overridden.
	n and name for this A/C. er defined data will be overric	lden.		
		5	Choose a	an icon
			-	🖣 🔺 📠 🛅
				2
Choose ar	nd icon and a name for	this A/C	HOUSE	and icon and a name for this A/G
	Name		^	
	NEXT			NEXT



5. Detect your remote control





6a. Android devices: The app will ask for the password of your networks and will automatically configure Sensibo Sky.

6b. iOS devices only: Connect to the device's access point as detailed in the next screen (each device creates a unique Access Point, you'll see the exact name)

No SIM 🗢	5:47 PM		▲Back to Sensibo	11:03 AM	* ■⊃
	Smart A/C Setup	? :	Settings	Wi-Fi	
Connect to you	ur smart A/C in Wi-Fi settings		Wi-Fi		
network for th	/C has created a temporary Wi ne setup process	-Fi	SENSIBO-I-1	6744	? 〔)
	iPhone's Wi-Fi settings the following smart A/C netwo	ork:	CHOOSE A NETWORK		
			Bezeq Free		२ (i)
			Bezeq-NGN_	F48705	🔒 🗢 🧻
Settings Wi-Fi			BezeqNGN_J	A19BC_2.4GHz_1	२ (i)
Joerung	3 WI-II		Electra Route	er	₽ 奈 (i)
Wi-Fi			hadarbarel		∎ ? (i)
CHOOSE A	NETWORK		nahala		₽ ╤ (j)
SENSIBO-	1 16744	〒 (j)	sensibo		🛾 🗢 i
SENSIBU-	-10744		Sensibo_elc		₽ ╤ (i)
Click	k here to go to network settin	gs	SENSIBO-I-9	7690	? (i)
Can't find this Please make	s network? sure that your A/C is plugged i	n.	TNCAP50B8	BC	? (i)
	k is still missing, <u>contact suppo</u>		Other		

7. Locate your local Wi-Fi network in the list and connect to it



No SIM	11:03 AM	* □-	No SIM	11:04 AM	* 🗖
	Smart A/C Setup	? :			
	t your Smart A/C to the interne local Wi-Fi network:	et, please		: your Smart A/C to the interr local Wi-Fi network:	net, please
Cassade	euno	ê 🤶	Cassade	euno	₽ 🤝
Electra I	Router	A 🤤	Elec	Enter Password	a 🤤
Electra	/R3420	£ 🗢	Elec	Selected network: sensibo	
hadarba	irel	9 🗢	hada	assword	•
Itach		۽ ھ	Itacł	Cancel OK	a 🤶
Jacksor	1	a 🤶	Jackson	ı.	۵ 🗢
nahala		A 🗢	nahala		ج ۵
noel		ê 🤤	noel		۽ ھ
sensibo		8 ?	sensibo		8 🗢
Sensibo	_elc	8 🗢	q w	ertyu	i o p
TNCAP5	50B8BC	?	a s	d f g h j	k I
Other			φz	xcvbn	m
	() REFRESH NETWORKS		123	space	return



8. Name your location and you're done!





Operating the Sensibo App

The main screen of each A/C has live information about temperature and humidity in the room, the current settings of the A/C and enables you to control your A/C from anywhere manually or by using Sensibo's in-app automations.



A/C settings

In the screen you can view Recent Events you and other users of this A/C performed, sync the A/C power state, change name and icon of this device, share it with family/friends/colleagues and remove this device from your Sensibo account.





Scheduling

With Sensibo you can automate your AC's on and off times. Select an AC to apply the schedule to, whether you'd like to turn it on or off, other AC settings like temperature, mode and fan level and the time to do the action. You can create multiple schedules for each AC and create schedules for all your connected ACs.





Geofencing and Anticipate my Arrival feature

Sensibo can turn on your AC automatically before you arrive when you enter a predefined geofence radius (1km/2km/5km/10km).

•••• GOLAN	T 🗢 12:18 PM -	🕇 💲 100% 🛄 +
🗸 Back	Anticipate my arrival	
MCE 2016	ő (5km trigger) 🖉	
Nahalat Bi	nyamin St 38-48 ,Tel Aviv-Ya	fo
in	side 4	
Sensibo (1 km trigger) 🖊	
9978 Fort	Hamilton Parkway	
AT	v's smart AC	\bigcirc
Stephen's	place (1km trigger) 💋	
1009 Nortl	n Creek Street ,Dewey	
	ring room	\bigcirc
Walter loc	ation (1km trigger) 💋	
תל אביב יפו,	רחוב הארבעה.	
Fr	igidaire at office222222323	333
W	alter 156	\bigcirc

Open API and integrations

Sensibo is open and can be integrated into other services. You can view our current integrations and read more about the API here: <u>bit.ly/sensiboAPI</u>



Sharing your AC with others

You can easily grant access to your AC to family members, friends, colleagues and more. Other users of the AC need to download and install the Sensibo app on their mobile device. To share your AC, go to the AC settings and select "Share this AC", then select how to share the access link - via email, IM apps, etc. Each invitation can be used one time only.





FAQ and Troubleshooting

How can I turn the A/C on or off?

You can turn the A/C on or off via:

1. The power button at the bottom of the main A/C screen



2. The power button in the locations/devices screen

Den		Ń
Sensibo main	Ĵ [:] 25.5° (∕) 43.4%	



How can I change the A/C state to cool, heat, etc.?

You can change the A/C state via the A/C state button in the main screen - clicking on the current A/C state will open a little fan with all available modes





How can I change the fan level of my A/C?

You can change the fan level via the fan button in the main screen clicking on the current fan level will open a little fan with all available levels





How can I set a timer for my A/C?

You can set a timer for a specific A/C via the timer button in the main screen - clicking on it will open a round dialer where you can set the amount of minutes/hours you want the A/C to turn on/off.





How can I change the name or icon of my A/C?

Go to the specific A/C's settings and hit "Change name and icon".

No SIM	†	11:44 AM	* 🗖
A	Central		Close
	Recent even	ts	
*	Sync A/C Po	wer State	
0	Change name	and icon	
4	Share this A/	с	
×	Remove from	app	



How can I invite other people to use my A/C?

If you want to grant access to your A/C to other people (family members, friends, colleagues, etc.) you can send a unique link via multiple channels - go to the A/C settings, choose "Share this A/C", select an app to send the invitation from and hit send.





How can I set and edit schedules for my A/Cs?

You can access your devices' schedules and create new ones via the locations/devices screen:



To edit an existing schedule, click on it in the list of schedules.



How can I delete a schedule?

Just swipe the schedule you want to delete to the right in the schedules main screen and confirm.





How can I setup another Smart A/C?

In the general settings (accessible via locations/devices screen) tap "Setup a new Sensibo device" to start the installation process again with another device.

No SIM	?		11:44 AM			* 🗖
		Gene	ral Sett	ings	C	Close
A	Anticipate	my arriva	al			
G	Setup a no	ew Sensib	o device			
*	Push noti	fications			(
ABC	Select la	nguage			Eng	llish
	Report a	problem				
0	About					
	Logout Signed in as u	user (user@dd	omain.com)			

How can I reset my Sensibo user password?

Via this page: <u>https://home.sensibo.com/password-reset/</u>



I get a "device is disconnected" notification in the app, what does it mean?

A few reasons can cause your smart A/C to appear as disconnected. Please click on the notification to learn the reason (in iOS devices you'll need to reconnect to the Smart A/C's network again).

Cannot join Wi-Fi network

No	sim 후	3:40 F	м	\$ = D
		mart A/C	Setup	? :
	Canno	ot join Wi	-Fi network	
	Your smart A/	c 🔇) Your rol	uter
	1.ls your Wi-Fi netw Check with your ph network. 2.Was the passwo	none that rd recentl	you can conn y changed?	
	Make sure you hav RECONNECT	e the con	EDIT SET	



This screen will appear when one of 3 scenarios happens:

- 1. The network is offline and the Smart A/C cannot join it
- 2. The password or name of the network were changed recently and the Smart A/C cannot join it with it's existing data that is outdated
- 3. The Smart A/C was reset on purpose to connect to another network

Android only - Network has no internet connection



This screen will appear when one of 2 scenarios happen, while the Smart A/C managed to connect to the network (correct name and password) but:

- 1. The network has no internet might be an issue with the Internet Service Provider
- 2. Some firewall or other security measures were changed and block your A/C from connecting



Android only - App cannot find your smart A/C's network

This screen will appear if your mobile phone cannot "see" the Smart A/C network when it scans the nearby networks - this can be caused by a few reasons:

- 1. The A/C is not connected to the power so the device cannot transmit any signals
- 2. The mobile phone is too far away from the Smart A/C so it cannot see it
- 3. The Smart A/C was previously configured and need to be reset remotely by the support





Android only - Cannot connect to your Smart A/C network

This screen will appear when your mobile phone tried to connect to the Smart A/C network (it appeared properly in the networks scan your mobile phone performed) but then couldn't complete the connection process.

This is usually caused by another device that connected to the device before your mobile phone managed to connect.

👻 🏄 🛢 12:30
Smart A/C Setup 🛛 😗 🚦
Cannot connect to your smart A/C network
Please make sure other devices are not connected to this A/C network.
The network can be connected only to one device at a time.
CANCEL



Smart A/C Installation issues

My Smart A/C cannot connect to my local network

- 1. Make sure that you connected Sensibo Inside to your network and that it the network is working properly (on your mobile phone, etc.). Sensibo Inside should have a steady blue light when it's connected to the internet properly. If it blinks it means there is a problem with the connection:
 - a. 2 blinks repeatedly: Sensibo Inside cannot connect to the network. This might be due to a password/name change, proxy/security changes in the network or just no signal from the network.
 - b. 3 blinks repeatedly: Sensibo Inside is connected to the network but receives no connection.
 - c. LED is off = Wi-Fi chip issue, restart installation process.
 - d. LED is on but no connection in app- server issue
- 2. Make sure that the A/C is connected to the power. If the A/C is not connected to the power, Sensibo Inside cannot connect to the internet and control the A/C.

A few reasons can cause your smart A/C to not be able to connect in the installation process.

Please click on the notification to learn the reason (in iOS devices you'll need to reconnect to the Smart A/C's network again).



Cannot join Wi-Fi network

No SI	M 🗟			3	3:40 F	м					*	D
			Sn	nart	A/C	Se	tup			?		
		(Canno	t joi	n Wi	-Fir	netw	/ork				
		Your si	mart A/C		8)	G	Your	route	-		
Ch		ur Wi-F with yo rk.								t to t	hi	5
		the pa sure yo							rd			
	I	RECONI	NECT				EDI	TS	етті	NGS		

This screen will appear when one of 3 scenarios happens:

- 1. The network is offline and the Smart A/C cannot join it
- 2. The password or name of the network were not entered correctly
- 3. The Smart A/C was reset on purpose to connect to another network



Network has no internet connection

No SIM 🗢		3:42 PM		*	-0				
	Smart	A/C Setu	ip	?					
1	No internet connection								
Your smar	<u> </u>	our router	Inter	net					
Try joining this have internet. Contact your IS 2.Do you have	Contact your ISP if no internet is available 2.Do you have a firewall? some firewalls could block your smart A/C from reaching the internet (<u>read</u>								
RECONN	ECT	E	DIT SETT	INGS					

This screen will appear when one of 2 scenarios happen, while the Smart A/C managed to connect to the network (correct name and password) but:

- 1. The network has no internet might be an issue with the Internet Service Provider
- 2. Some firewall or other security measures were changed and block your A/C from connecting



Certification

This device complies with Part 15 of the FCC Rules.

Operation is subject to the following two conditions:

(1) this device may not cause harmful interference, and

(2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

The socket-outlet shall be installed near the equipment and shall be easily accessible

