



NAMEPLATE DATA	EXTERNAL CONNECTION DIAGRAM	NOTES
MODEL: K48M2N110C2 CUST PN: UST1202 HP: 2 SF: 1.1 ROT: CCWPE RPM: 3450 TYPE: UAK CODE: H FORM: FRAME: 56J VOLTS: 208-230/115 AMPS: MAX AMPS: 10.4-9.8/19.6 SF AMPS: - PH: 1 HZ: 60 INS: B AMB: 50°C DUTY: CONT ENCLOSURE: ODP THERMALLY PROTECTED	<p>GRD GREEN (GROUND) HIGH VOLTAGE SHOWN. ROTATE DIAL CCW TO 115 FOR LOW VOLTAGE. USE COPPER CONDUCTORS ONLY. INSTALL MOTOR WITH VENTS DOWN. ACCEPTABLE FOR FIELD WIRING</p>	1. FINISH PAINT TO BE SATIN BLACK. 2. .44[11.1] WRENCH FLATS ON SHAFT-FOR ACCESS TO THIS WRENCH FLAT REMOVE END COVER. 3. STAINLESS STEEL SHAFT EXT. 4. LIMITS ON AMPLITUDE OF VIBRATION MEASURED AT BEARING HOUSING = .001[.03]. 5. CONNECTED FOR HIGH VOLTAGE QUICK VOLTAGE CHANGE PLUG INCLUDED ON THE TERMINAL BOARD.

A	PERFORMANCE CURVE		APPROVED SAMPLE	
	K48M2W16			
	UL COMPONENT		CSA	
	FILE#	CCN#	FILE#	GUIDE#
	E25022	XEWR2	LR43341	4211-01
	CUSTOMER	DIST. SERVICES		

DRAWING REVISION G ECO ECO-0165900 ECO DESCRIPTION SEE ECO	REVISION BY M.RODARTE APPROVED BY -	DATE 05-01-2019 DATE -	TOLERANCES UNLESS OTHERWISE SPECIFIED DEC. INCH mm ANGLE .X $\pm$ 0.1 [1.27] $\pm$ 0.5° .XX $\pm$ 0.02 [0.51] $\pm$ 0.13° .XXX $\pm$ 0.005 [0.127] $\pm$ 0.013° .XXXX $\pm$ 0.0005 [0.0127] $\pm$ 0.0013° REMOVE BURRS & BREAK SHARP EDGES .003/.015 [0.076/.381] CORNER FILLETS .02 [0.51] MACHINED SURFACES 125/1000 3.2/254 mm SHOWN IN [BRACKETS]	DRAWN BY: LC DATE: 06-19-2009 APPROVED BY: LX DATE: 06-19-2009 REFERENCE -	THIRD ANGLE PROJECTION	REGAL Regal Beloit America, Inc.	DESCRIPTION MODEL-PFHP-48FR OUTLINE	MATERIAL -	PROCESS/FINISH -	SIZE DWG NO C UST1202	SHEET 1
---------------------------------------------------------------------------	----------------------------------------------	---------------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------------------------------------------------------------------------------------	------------------------	----------------------------------	-------------------------------------------	---------------	---------------------	--------------------------	------------