

Blizzard Lighting, LLC

Phone: 1.866.493.6025
Fax: 1.866.870.0031
Email: info@blizzardlighting.com
Website: http://www.blizzardlighting.com

ROKBOX™ 5 RGBAW

The RokBox[™] 5 - Revolutionary high powered 5-in-1 LED wash fixture

The box... one of the most useful, time tested, and attractive 3-dimensional shapes ever created is once again new and improved!

With the addition of 18x 15-watt RGBAW 5-in-1 LEDs, advanced electronics, and dual hanging brackets with secure grip locking knobs, the RokBox™ 5 is sure to be a great addition to your lighting rig!

It features 4/5/9 or 10 DMX channel modes, which means it works great with any type of controller, including popular 4-channel controllers. You'll have full control of all that RokBox™ 5 has to offer such as RGBAW color mixing, 31 built-in programs, ultra smooth flicker-free 32-bit dimming (5 user-selectable dimming curves), and even easy HSV color mixing ability in 4-channel mode.

The super-easy to use built-in 4-button LED control panel also allows total control over the fixture including master/slave settings, sound active mode, built-in programs, auto mode, custom RGBAW color mixing, and user adjustable fade/strobe effects for a totally rocking light show!

It also comes equipped with industry standard powerCON® compatible power input/output connections & 3-pin DMX connections which are all strategically placed on the back of the unit in a way that allows you to use the RokBox™ 5 in ANY position, including flat on the floor. This makes the RokBox™ 5 a perfect solution for any of your uplighting and/or truss warming needs!

Check out the RokBox $^{\text{\tiny{TM}}}$ 5 today. It's hip to be square!

Control Features

- RGBAW color mixing via 18x 15W Red/Green/Blue/Amber/White 5-in-1 LEDs
- Built-in color & chase macros via DMX
- Built-in automated and sound active programs via master/slave
- RGBAW color mixing ability in standalone mode
- 3-pin male input and 3-pin female output
- Rugged and well-built (It hits the gym regularly)
- Dual mounting brackets for positioning flexibility
- · Flicker-free constant-current 400hz LED driver
- 3-pin male input and 3-pin female output
- PowerCon[™] compatible AC power In/Out connectors





DISCLAIMER:

The power connector fitted to the fixture and fixture cord are designed for compatibility with products manufactured by Neutrik AG, Neutrik USA and their related entities, however they are not manufactured by, affiliated with or endorsed by Neutrik AG, Neutrik USA, or any related entity. Neutrik* and powerCON* are registered trademarks of Neutrik AG.

Additional Features

- Beam Angle: 25 degree optics standard, 26 degree beam, 30 degree field
- Light source: 18x 15W 5-in-1 LEDs 100,000 hours.
 Operating Voltage: 90-230VAC 50-60Hz
- Power Consumption: 154W Max
- Luminous Intensity: 27,000 LUX (Full RGBAW)
 @1M

Weight & Dimensions

- Length: 9.22 inches (234 mm)
- Width: 6.5 inches (165 mm)
- Height: 8.98 inches (228 mm)
- Weight: 7.28 lbs (3.3 kg)

Warranty

 2-year limited warranty, does not cover malfunction caused by damage to LED's.

ROKBOX™ 5 RGBAW Luminous Intenstiy

| RokBox 5 RGBAW | 1M | 2M | 5M |
|------------------|--------|--------|-------|
| Red | 6,300 | 2,200 | 300 |
| Green | 6,700 | 2,400 | 400 |
| Blue | 8,000 | 2,900 | 500 |
| Amber | 4,300 | 1,300 | 200 |
| White | 7,700 | 2,.700 | 400 |
| All (Full RGBAW) | 27,000 | 9,600 | 1,400 |







