



## SUNBOLT LED SPOTLIGHT OPERATING INSTRUCTIONS

- 200-1006 Sunbolt 6 - 18°
- 200-1008 Sunbolt 6 Tac - 8°
- 200-1009 Sunbolt 6 Tac-Strobe 8°



The SUNBOLT Spotlight is a powerful spot/search light. Key features include:

- Fully submersible to 24 ft / 7 m
- Instantly turns on to Low Light Level
- Minimal Projected Heat, and no warm up/cool down is needed

### IMPLEMENTATION

1. Unit mounts on a standard 3/4" inch diameter post.
2. Turn Diamond Knob clockwise to secure to post.
3. Turn Diamond Knob on side of head counter-clockwise to loosen brake, holding the back of the unit by the handle.
4. Adjust up/down and tighten brake clockwise.



### POWER SOURCE: AC Power Supply



- Dimensions: 12" x 8" x 5" (305 x 203 x 127 mm)
- 100 – 240 VAC 50/60 Hz Power Supply
- 220 Watt Power Consumption
- Power Switch
- On LED Indicator
- Dimming Knob
- Insert keyed connector on Power Supply, and secure by turning ring cap clockwise (below)

### OPERATIONAL MODES

The SUNBOLT Spotlight can cycle through -3- Operational Modes, by pushing the black rubber button switch at the center-top of the Power Source.



All Sunbolt Models will automatically turn on in Low Mode. Modes are as follows:

Mode	Light Output
Low	3,000 Lumen
Medium	7,000 Lumen
High	11,000 Lumen

Please see the two DMX connectors for external control.



### P/N 200-1009 ONLY:

Pressing one more time (after High Mode) will activate the FoxFury Turbo Strobe mode.  
NOTE: This mode may induce vertigo. Prolonged exposure has shown to cause vomiting as well.

## **PRODUCT DURABILITY**

- Waterproof: Fully submersible to 24 feet / 7 meters
- Impact Resistant: May survive fall to the ground from 6' / 180 cm

## **CARE & MAINTENANCE:**

*Please Note: The Sunbolt casing will get warm, reaching temperatures of around 195°F / 91°C in the hot sun, and after being on for many hours. Keep this in mind as you handle the unit.*

Your FoxFury is a professional tool, and regular maintenance and care of your Sunbolt will maximize performance for you.

As needed, remove dirt and debris as this will ensure that your Sunbolt will continue to emit maximum light.

## **ADDITIONAL OPTIONS:**

### **DC Converter**

Permits performance with DC inputs from 11VDC to 30VDC. Fits most batteries on vehicles and boats.



### **Battery Pack:**

- Lithium Ion
- 600 WH (3 hrs at full intensity)

## **WARNINGS:**

### **IMPORTANT:**

FoxFury, LLC is not responsible for the incorrect use of any FoxFury Lighting product.

- Lights are strong enough to cause damage to the human eye.
- Do not stare into LEDs for long periods of time or from a close range (less than 2 feet).
- FoxFury, LLC is not responsible for any injury or damage caused during the use of this product.
- Usage of this product must be supervised by an adult if it is being used by a minor.
- Any FoxFury product should be operated at speeds safe enough to maneuver around surrounding obstacles.
- Do not use under the influence of drugs or alcohol.

## **STROBE WARNING**

FoxFury's Turbo Strobe is purposely designed to induce disorientation. Prolonged viewing may produce vertigo or even vomiting. Note that the frequencies implemented are well below the ones reported to cause photo-induced seizures. As with all products, use common sense while operating.

## **WARRANTY & CUSTOMER CARE**

### **Warranty**

Seller warrants to Buyer that for a period of two years following the delivery of product to Buyer, the Products will be free from defects in material and workmanship and will function in substantial compliance with the manufacturer's written specifications thereof. Buyer's exclusive remedy shall, in any case, be limited, at the Seller's election, to: A) Repair or replacement of the defective products; B) Refund of the purchase price thereof or; C) Crediting of the same against future purchases by Buyer. THE FOREGOING WARRANTY IS THE ONLY WARRANTY MADE BY SELLER WITH RESPECT TO THE PRODUCTS. THERE ARE NO REPRESENTATIONS OR WARRANTIES OF ANY KIND BY THE SELLER, EXPRESS OR IMPLIED, WITH RESPECT TO THE CONDITION OR PERFORMANCE OF THE PRODUCTS, INCLUDING, BUT NOT LIMITED TO, THEIR MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.

**Warranty excludes any issues arising from use, abuse, or general wear and tear.**

### **Customer Care**

1. The damaged part or product must be returned to FoxFury, LLC **PRIOR TO** any repair or replacement. Shipping costs are the responsibility of the claimant.
2. You must obtain a return authorization (RMA) number from FoxFury, LLC prior to returning products. FoxFury, LLC is not responsible for any damage incurred while in transit.
3. Customer will be required to show proof of purchase – No Exceptions.
4. Any modifications to light, cable or battery pack automatically voids all warranties on this product.

All warranty inquiries should be directed to FoxFury's Customer Service Department to handle all warranty/repair-related inquiries.

FoxFury, LLC  
Vista, CA 92084 USA  
Tel: 760.945.4231  
Fax: 760.758.6283  
Email: [custserv@foxfury.com](mailto:custserv@foxfury.com)  
[www.FoxFury.com](http://www.FoxFury.com)