




OPERATION GUIDE

1. POWER ON/OFF

Long press power button "(1)" for 2-3 seconds to power on/off.

2. BLUETOOTH CONNECTION

It will enter to Bluetooth mode after power on, and the blue indicator light will flash. Then choose "Kasita" from devices list. You will hear voice prompt once it connected, and the blue indicator light will long on. Then you can start to play your music. Double press "(1)" quickly to disconnect Bluetooth connection





3. VOLUME CONTROL

Short press "+" to increase volume, short press "-" to decrease volume; when its volume increase to maximum volume, you will hear "Beep" voice prompt. PREVIOUS/ NEXT SONG CONTROL:

Long press "+" for 2 seconds to play next song, long press "-" for 2 seconds to play previous song on Bluetooth mode.

OPERATION ON PLAYING STATUS:

Short press "" to pause playing, press again to start playing on Bluetooth mode; Short press "()" to mute, press again to un-mute on Aux mode. EQ SWITCH:

Default standard sound effect. Double press "**M**" to switch EQ, Standard→Outdoor → 3D sound effect. The Bluetooth indicator light will flash when switch EQ on Bluetooth mode. The AUX indicator light will flash when switch EQ on Aux mode. USB indicator light will flash when switch EQ on USB mode.


Default Bluetooth Mode. Short press "M" to switch Mode, Bluetooth → Aux.

4. HANDSFREE CALL

When Bluetooth connected successfully, speaker enter into Bluetooth handsfree status automatically when you call at that time. When call coming, short press " 1" to pick up, press again to hang up. Quick press twice to reject the call.

5. TWS CONNECTION

If you have two "KASITA", power on both of them, they will enter to Bluetooth mode. Long press each of their " M " button, the white TWS indicator light will flash. Then they will connect with each other automatically. After they connected successfully, both of their white indicator light will long on. The master model's blue indicator light will keep flashing, the sub-master model's blue indicator light will long on. Repeat the Point 2 Bluetooth Connection, connect the model with your phone. After the two models successfully connected with your phone, both of them will play music at the same time.



Remark: 1. Two speakers are needed and both must be on Bluetooth mode.

2. Before TWS pairing, don't pair any other device for speaker.

6. AUX-IN MODE Use 3.5mm Aux cable to connect "KASITA" and device, it will switch to Aux mode automatically, the green indicator light will on. Then you can play music immediately. Status Indicator light 7. CHARGING Don't use no safety-certified adapter • Use 5V/2A or above 2A adapter 1. Pls charge for the speaker when hearing low battery prompt voice. 2. Red indicator is on when charging, and it is off after full charge. 3. Short press the power button before using USB-A function if speaker is in off status Status Indicator light

8. POWER SAVINGS Under below situation, the speaker will power off to save battery power: On BT mode, without any connection with any device for 10 minutes; Long press " (b) " 2-3 seconds to power on after that. 9. USB PORT FEATURES Your speaker has an integrated USB port which has two functions: 1) For playing music files stored on a USB drive: Simply insert a USB drive with pre-loaded mp3/audio files into your speaker's USB port. A white LED will illuminate when in USB disk mode. 2) For charging smartphones and USB-powered devices: Simply insert your device's USB charging cable into the speaker's USB port, then short press power button to charge your device. The charging output is 2A. Please use this feature only as a last resort (if your phone's battery is about to run out) as it will deplete the battery of the speaker thus reducing the music playback time RoHS (E FC & A

FUNCTION INSTRUCTIONS TWS Indicator Light Status Indicator Light Blue indicator light will on when power on, and enter to Bluetooth mode automatically. And the blue indicator light will quick flash (on Bluetooth devices searching status) Power on Green indicator light will on when connected by 3.5mm audio cable Blue indicator light on when Bluetooth connected successfully Bluetooth Blue indicator light keeps flashing if your Bluetooth devices out of AUX mode Green indicator light will on when connected by 3.5mm audio cable U Disk mode White led indicator light will be on TWS indicator light will quick flash when it is on TWS mode TWS indicator light long on when connected successfully TWS mode Red indicator light will on while charging; red indicator light will off Charging when charging finished. Low battery Red indicator light will quick flash when battery low Speaker will power off automatically when battery lower than 10%, and you will hear power off voice prompt.

SPECIFICATIONS	
Product Name	KASITA
Model Name	TR-BS221B
Bluetooth Version	5.0
Battery Capacity	7.4V / 3600mAh
Playing Time	10~12h
Charging Time	3~4h
Speaker Unit	20Wx2 + 10Wx2 = 60W
Charging Current	5V/2A
USB-A Port	5V/2A output (max.)
Product Size	310 x 152 x 118mm
Product Weight	2164g±50

FAO

Q: What kind of charger should we use for the speaker?

A: All common USB chargers can be used, while we suggest the ones 5V/2A or above 2A. Q: What if there is noise or discontinuous sound during playing?

The speaker can be normally used within 10m under no obstruction environment.
 If it is beyond 10m or with obstruction, there might be noise or discontinuous sound.
 C. Why the speaker power of automatically after power on but no Bluetooth disconnection?

A: When there is no bluetooth pairing in 10 minutes, the speaker will shut

A. Write titler is no doescorin paint in finitious, it is speake with short of control of the co

O: What is the working sequence of the speaker?

A: Default mode is Bluetooth mode but when insert in AUX in cable,it will be AUX IN mode.

The speaker cannot be started up in a normal situation.
 A: Please plug in the charger and try in a few minutes or try to long press power button 10-30s to reset.

Please read this manual carefully before use and keep it properly.

For the first use, please fully charge the product.
 Pls use certified adapter that has passed national safety certification.

If you do not use the product for a long time, be sure to charge it once within a month at least to maintain its performance.

Do not use this product in an extremely cold or hot environment, such as temperature

beyonds the range of 5 °C-35 °C. If use it beyond the above range, the product may stop automatically to protect the internal circuit.

When charging it in a high temperature environment, the product may automatically stop charging to protect
the battery. At this time, the charging indicator usually flashes quickly to indicate that the charging

environmental temperature or the product internal temperature is too high.

7. Storage environment temperature: -5 ~ 35 C RH < 70% (recommended 25 C ± 5).

Important safety instructions:

 Do not disassemble or repair this speaker personally, otherwise it may cause product damage or personal injury.

2. Do not use it in dusty, humid, dry, and high-temperature environ

3. Do not place this product near a heat source, or a place with direct sunlight,

a lot of dust, or mechanical vibration.
 In order to reduce the risk of fire, please do not cover this product

with newspapers, tablecloths, curtains etc., during use.

5. If the product has a waterproof feature, please do not exceed the

If the product has a Waterproof readure, please on ont exceed the
nominal parameter range when using it.
 When the product is damaged such as the power cord or plug is damaged, liquid enters
or objects fall into the device, unable to operate normally or falls, it must be repaired.
 When the product is fully charged, do not connect it to the charger for further long
time charging. The maximum ambient temperature should not exceed 40°C.

This speaker supports mobile phones/ tablets/ PCs etc. Here this User Manual is