



Nothing But LED's Commercial-Grade retrofit downlights are the most innovative and feature rich product of its kind. This new 2023 model offers CCT adjustable 2700K / 3K / 3500K / 4K / 5K and wattage adjustable. The LED Commercial Down Light produces lumens up to 4000Lm, which is perfect for ceilings up to 16ft height. Commercial-Grade retrofit downlight is perfect for retrofit or new construction.

Product Features

Up to 110 lumens per watt
Wattage Adjustable
CCT adjustable 2700K / 3K / 3500K / 4K / 5K
Available in 4", 6" & 8"
Integral heat sink

Input Voltage 120-347Vac 0-10V Dimming capability ETL & ES Listed 5 Years Warranty



SKU#	Model #	Wattage Adj.	Lumens	CCT Adj.	Size	Input Voltage	Dimming	Certifications
1560668	FXF01001-A-A001	9W/13W/18W	2110Lm	2700K / 3K / 3500K / 4K / 5K	4"	120-347Vac	0-10V	ETL & ES
1560644	FXF01002-A-A001	13W/19W/27W	3000Lm	2700K / 3K / 3500K / 4K / 5K	6"	120-347Vac	0-10V	ETL & ES
1560669	FXF01003-A-A001	18W/27W/36W	4000Lm	2700K / 3K / 3500K / 4K / 5K	8"	120-347Vac	0-10V	ETL & ES

SKU #. 1560668 / 4" Specifications

Parameter	Description	Value
	Model #	FXF01001-A-A001
	Wattage Adjustable	9W / 13W / 18W
	Lumen	2110LM
General Performance	Lumen Efficacy	Up to 110LM/W
T CITOTITIANICE	Color Temperature	2700K / 3000K / 3500K / 4000K / 5000K
	CRI (Ra)	>80
	Beam Angle	120° Degree
	Diffuser Type	PC Lens
	Input Voltage	120-347Vac
	Frequency	50/60Hz
Electrical	Dimming	0-10V Dimming
	Power Factor	≥0.9
	Driver Surge Protection	N/A
	Flicker Percent	<30%
	Operating Temperature	-20°C to 45°C
	Operating Humidity	N/A
	Storage Temperature	-25°C to 40°C
	Storage Humidity	N/A
Physical	LED Brand	Seoul / Everlight
	LED Type	LED Built-in
	LED QTY	
	Housing	AL
	Housing Color	White
	IP Rating	Damp Location
Qualification	Warranty	5 Years Warranty



SKU #. 1560644 / 6" Specifications

Parameter	Description	Value
	Model #	FXF01002-A-A001
	Wattage Adjustable	13W / 19W / 27W
	Lumen	3000M
General Performance	Lumen Efficacy	Up to 110LM/W
renormance	Color Temperature	2700K / 3000K / 3500K / 4000K / 5000K
	CRI (Ra)	>80
	Beam Angle	110° Degree
	Diffuser Type	PC Lens
	Input Voltage	120-347Vac
	Frequency	50/60Hz
Electrical	Dimming	0-10V Dimming
	Power Factor	≥0.9
	Driver Surge Protection	N/A
	Flicker Percent	<30%
	Operating Temperature	-20°C to 40°C
	Operating Humidity	N/A
	Storage Temperature	-25°C to 40°C
	Storage Humidity	N/A
Physical	LED Brand	Seoul / Everlight
	LED Type	LED Built-in
	LED QTY	64 Pcs
	Housing	AL
	Housing Color	White
0 116 11	IP Rating	Damp Location
Qualification	Warranty	5 Years Warranty




SKU #. 1560669	/ 8" S	pecifications
----------------	--------	---------------


Parameter	Description	Value
	Model #	FXF01003-A-A001
	Wattage Adjustable	18W / 27W / 36W
	Lumen	4000M
General Performance	Lumen Efficacy	Up to 110LM/W
Periormance	Color Temperature	2700K / 3K / 3500K / 4K / 5K
	CRI (Ra)	>80
	Beam Angle	110° Degree
	Diffuser Type	PC Lens
	Input Voltage	120-347Vac
	Frequency	50/60Hz
Electrical	Dimming	0-10V Dimming
	Power Factor	≥0.9
	Driver Surge Protection	N/A
	Flicker Percent	<30%
	Operating Temperature	-20°C to 45°C
	Operating Humidity	N/A
	Storage Temperature	-25°C to 40°C
	Storage Humidity	N/A
Physical	LED Brand	Seoul / Everlight
	LED Type	LED Built-in
	LED QTY	
	Housing	AL
	Housing Color	White
	Rating	Damp Location
Qualification	Warranty	5 Years Warranty



Correlated Color Temperature (CCT)





Dimensions






Dimensions










SKU: 1560668 - 4"


Photometric Data





SKU: 1560644 - 6"


Photometric Data





SKU: 1560669 - 8"


Photometric Data





Product Structure







Installation

SAFETY PRECAUTIONS:

READ ALL INSTRUCTIONS

WARNING - RISK OF FIRE OR ELECTRIC SHOCK. INSTALLATION REQUIRES KNOWLEDGE OF LUMINAIRE ELECTRICAL SYSTEMS. IF NOT QUALIFIED, DO NOT ATTEMPT INSTALLATION AND CONTACT A QUALIFIED ELECTRICIAN.

WARNING - THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH APPLICABLE INSTALLATION CODES BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.

WARNING - INSTALL THIS KIT IN ACCORDANCE WITH THE INSTALLATION INSTRUCTIONS ACCORDING TO THE DIMENSIONS AND SUPPLY VOLTAGE AND AMPERAGE RATINGS SHOWN.

DO NOT INSTALL THE LUMINAIRE NEAR ANY HEAT SOURCE.

TO AVOID INJURY OR DAMAGE TO THE LUMINAIRE, PLEASE ENSURE THAT THE POWER LEADS AND SCREWS ARE SECURE BEFORE CONNECTING POWER.

ALWAYS ENSURE THAT POWER IS OFF, AND THE LUMINAIRE HAS COOLED, BEFORE PERFORMING ANY MAINTENANCE, CLEANING, OR ADJUSTMENTS TO THE LUMINAIRE.


FCC NOTICE

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment on and off, the user is encouraged to try to correct the interference by one or more of the following:

- 1. Reorient or relocate the receiving antenna.
- 2. Increase the separation between the lighting unit and receiver.
- 3. Connect the lighting unit into an outlet on a circuit other than the outlet which the receiver is connected.
- 4. Consult the dealer or an experienced radio/TV technician for assistance.

NOTE: Please note that changes and modifications are not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Conforms to standard CAN-ICES 005(B) /NMB-005 (B)



	PRODUCTS COVERED									
Model	CCT Adjustable	Lumen output	Wattage Adjustable	Α	В	С	Min. Cutout	Max. Cutout		
4" CCT	2700/3000/3500	1000/1500/2000(LM)	9W/13W/18W	4.33"	5.91"	4.02"	4.33"	5.51"		
6" CCT	/4000/5000(K)	1500/2000/3000(LM)	13W/19W/27W	5.91"	8.27"	4.41"	5.91"	7.48"		
8" CCT	/4000/3000(K)	2000/3000/4000(LM)	18W/27W/36W	7.48"	10.24"	4.76"	7.48"	9.45"		



Installation


ALWAYS TURN OFF THE POWER SUPPLY FROM MAIN CIRCUIT BREAKER FIRST!


THERMAL RADIATION SPACE AND IRRADIATION DISTANCE MUST BE ENSURED. THE HEIGHT OF THE FIXTURE SHOULD BE NO LESS THAN 100MM. OPEN A HOLE IN CEILING ACCORDING TO CUTOUT SIZE OF THE LAMP.

CONNECT AC AND DC WIRES CORRESPONDINGLY AS SHOWN IN FIGURE 2.

BEND BACK THE SPRING CLIPS THEN PUSH THE LAMP INTO THE HOLE.

INSTALLATION COMPLETED. SWITCH ON.






ELECTRICAL CONNECTIONS- STANDARD LUMINAIRE

Make the following Electrical Connections:


- a. For 120-347V connect the black fixture lead to the voltage supply or Hot 1.
- b. For 120-347V connect the white fixture lead to the neutral supply or Hot 2.
- c. Connect the green or green/yellow supply ground lead to the junction box
- d. If 0/1-10y Dimming is used, connect the violet lead to the supply positive dimming lead. If dimming is not being used ensure to cap off the violet lead. For dimming connections, use Class 1 wiring methods.
- e. If 0/1-10V Dimming is used, connect the grey lead to the supply negative dimming lead. If dimming is not being used ensure to cap off the grey lead. For dimming connections, use Class 1 wiring methods.




^{**} Connect the green or green/yellow supply ground lead to the junction box



Wiring Diagram





Packaging								
SKU#.	Box Type	Product Size	Dimension (Inches)	Qty	Net Weight	Gross Weight		
1560668	Inner Box	4"	7.28 X 7.25 X 4.60	1				
1300008	Outer Box	4"	15.47 x1 4.76 x 8.11	6				
1560644	Inner Box	6"	8.46 x 8.46 x 5.03	1	1.16 LBS	1.52 LBS		
1300044	Outer Box	6"	26.38 x 9.29 x 11.02	6	7.01 LBS	10.07 LBS		
1560669	Inner Box	8"	10.43 x 10.43 x5 .43	1				
1300009	Outer Box	8"	21.77 x 17.24 x 11.26	6				



Application Image





Warranty

5 Years Warranty