# CAST LANDSCAPE<sup>®</sup> Old world craftsmanship...tomorrow's technology<sup>®</sup>

## CAST Savannah Area/Path Light (CSA1CB, CSA1LED2) Product Information

## CAST Savannah Area/Path Light - Perfect for Pathways, Gardens, and Driveways



#### **Description** -

This rugged and decorative solid bronze path/area light provides a soft glare free illumination. Since illumination is provided directly from the lamp and reflected from the hat, this fixture provides a brighter illumination than other fixtures. This fixture is available in drop-in LED (CSA1CB) and integrated LED (CSA1LED2). Existing installations of the CSA1CB can be converted to LED by purchasing the CAST LED Path Light Module (CSWLED2).

#### Features -

- Easily converted to intedgrated LED by adding the CSWLED2 Module
- Solid bronze hat and vase
- Large SOLID BRONZE talon mount stake with three 1/4" x 7" stainless steel spikes
- Heavy-gauge copper stem
- Pre-wired with 35' tin-coated No-Ox<sup>®</sup> marine grade wire
- High-temp socket
- Spider Splice<sup>®</sup> ready

#### Uses -

Suitable for lighting walkways, planting beds, and other areas.

CSA1CB

CSA1LED2

#### Construction: -

Solid bronze hat, arm, and post top; SOLID BRONZE stake; heavy-gauge copper stem; 35' tin-coated #18-2 No-Ox<sup>®</sup> marine-grade wire.

#### **Dimensions:** -

24" tall x 8.5" wide (post to shroud) Stake: 8"

#### Lamp Specifications: -

CSA1CB: 2.5W, 9-20 volt operating range, S8 LED Lamp (SL3156250L) (included). Halogen Option: 12V, 25W S8 wedge-base - 35W max. (C3156K). CSA1LED2: Voltage Range: 1-24V, .4 Amps, 4.41 Watts, Power Factor: .91, Volt Amps: 4.85, CRI: 82, Color Temp: 2737°K, Fixture Lumens 200, Max. Candela 94, L-70 62,000

## Hrs.

Listing: -UL 1838 listed. Environmental: RoHs, FCC Class B Conducted and Radiated.

