

Step Lite Solid Eyelid Square


PROJECT:		
TYPE:		
SOURCE:		
NOTES:		

PURELED SPECIFICATIONS (C UL) US




LED Chip	Cree XHP-50-2 Plug and Play field replaceable LED board
Luminaire Output	600 Lumens @ 1050mA (6 watts), 420 Lumens @ 700mA (4 watts), 240 Lumens @ 350mA (2 watts), delivered from luminaire with unobstructed beam.
Lumens Per Watt	100 Lumens @ 6 watts minimum, delivered from luminaire with unobstructed beam
CRI (3000K)	90+
Colour Temperatures	2700K, 3000K, 4000K
Beam Angles	15, 25, 38, 60
Ingress Protection	IP67
Warranty	Electronics = 5 years Body Cop/SS = 10 years Body Aluminium = 5 years
Standards	AS/NZS 61046 cUL 1838, 2108 CSA C22.2 No.250.7, No.250.0-08 CE





PRODUCT CONFIGURATION

Please fill in appropriate codes into boxes provided



Click here for Remote Power Supply Guidance Charts



HUNZA FACTORY

130 Felton Mathew Ave Auckland 1072 New Zealand

Ph: +64-9-528 9471 Fax: +64-9-528 9361 hunza@hunza.co.nz www.hunzalighting.com

INTERNATIONAL CONTACTS: http://www.hunzalighting.com/contact.php

Specifications may change without notice. This document contains proprietary inforr of Hunza. Its receipt or possession does not convey an rights to reproduce or disclor

LUMINAIRE CONSTRUCTION

CNC machined from one of the following metals:

Aluminium:

Body: high corrosion resistant 63.5mm (21/2") x 10mm (3/8") aluminium.

Flange: 90mm (31/2") solid aluminium rod. End cap: solid aluminium 63.5mm (21/2") rod with chromate substrate and high UV resistant polyester powder coat.

Colours:

Black, Bronze, Silver Star, White, White Birch, Olive Green, Dark Grey, Corten.

Body: 63.5mm (21/2") x 10mm (3/8"). Flange: 90mm (31/2") solid copper rod. End cap: solid copper 63.5mm (21/2") rod.

316 Stainless Steel:

Body: 63.5mm (21/2") x 10mm (3/8"). Flange: 90mm (31/2") 316 stainless steel rod. End cap: 316 stainless steel 63.5mm (21/2") rod.

Gaskets:

Silicone, iron impregnated 220°C (428°F)

Step Lens:

10mm (3/8") extra clear, low iron, flush fit, shatter resistant glass. Lifetime warranty.

Mounting:


Designed to fit through a 66mm (25/8") hole and be fixed into position by two screws in the flange or a Step Lite Canister (see accessories) can be used which maintains the aesthetic look of the flange by eliminating the two screw holes in the flange.


Luminaire Weight:

Low voltage Alum: 0.465kg (1lb) Cop: 1.340kg (2lb 15oz) SS: 1.055 (2lb 5oz)

ACCESSORIES







Hex Cell Louvre


Deck Canister

Step Lite & Stainless Steel Canister


BEAM ANGLES

High efficiency PMMA TIR lenses. Field replaceable

IES files available for download: hunzalighting.com/downloads



WIRING GUIDE



Diagrams are a guide only, wire colours and polarity may change depending on fixture and country

Available for download: hunzalighting.com/downloads

