# 6201LED OXFORD SERIES



DIMENSIONS 18" Ø 42" to 96' TALL



LUMEN LIFE SPAN RANGE L70 MINIMUM 520-590 100 000 HOURS



JOB NAME

CLICK

FOR FAQ's

FAQ

FIXTURE TYPE

MEMO

|       | BUILD A PART NUMBER                                |     |     |      |        |                   |             |                  |                   |        |
|-------|--|-----|-----|------|--------|-------------------|-------------|------------------|-------------------|--------|
|       | ORDERING EXAMPLE: 6201LED-48"-1L40TS-MDL07-CL2/BKT |     |     |      |        |                   |             |                  |                   |        |
| Model | Overall<br>Height                                  | LED | CCT | Туре | Driver | Option Chain Loop | Option Fuse | Option Photocell | Option Receptacle | Finish |
|       |  |     |     |      |        |                   |             |                  |                   |        |

| Model• 620ILED• 620ILED-QR   | <ul> <li>USB IB<sup>3</sup> 15 Amp duplex USB/Receptacle com-<br/>bo in pole base, includes mouse hole<br/>on door for wire access (NON-GFI)</li> </ul>                  | - |
|--|--|---|
| Overall Height (In Inches) •" (Available from 42" to 96")                    | <sup>1</sup> Ships loose for installation in base.<br><sup>2</sup> Accessory requires 48″ minimum height.<br><sup>3</sup> Cannot be used with QR (Quick-Release) option. |   |
| LED<br>• IL  | Finish<br>Standard Finishes <sup>4</sup> (Click here to view paint finish sheet)   |   |
| CCT - Color Temperature (IK)<br>• 27(00) • 30(00) • 35(00) • 40(00) • 50(00) | BICT Black Textured     WHT White Textured     PGT Park Green Textured   |   |

#### Type

TS (Symmetric)

#### Driver

• MDL07 (120V-277V, 700mA) • MDH07 (347V-480V, 700mA)

#### Options (Click here to view accessories sheet)

- CL1 Single Chain Loop
- CL2 Double Chain Loops at 180°
- FHD<sup>1</sup> Double Fuse and Holder
- PCD<sup>2</sup> Electronic Button Photocontrol, mounted on an access door (120V-277V)
- PCD4<sup>2</sup> Electronic Button Photocontrol, mounted on an access door (480V)
- GFI LPIUC<sup>2</sup> 15 Amp duplex GFCI receptacles with a low-profile in-use cover
- GFI IUC<sup>2</sup> 15 Amp duplex GFCI receptacles with a standard in-use cover
- USB LPIUC<sup>2</sup> 15 Amp duplex USB/Receptacle combo with a low-profile in-use cover (NON-GFI)
- USB IUC<sup>2</sup> 15 Amp duplex USB/Receptacle combo with a standard in-use cover (NON-GFI)
- GFI IB<sup>3</sup> 15 Amp duplex GFCI receptacle in pole base, includes mouse hole on door for wire access

SternbergLighting

ESTABLISHED 1923 / EMPLOYEE OWNED

- ABZT Architectural Medium Bronze Textured DBT Dark Bronze Textured
- <sup>4</sup>Smooth finishes are available upon request.

#### **Sternberg Select Finishes**

- VG Verde Green
- Swedish Iron
- OWGT Old World Gray Textured

#### Custom Finishes<sup>5</sup>

- CM Custom Match
- OI Old Iron
- RT Rust • WBR Weathered Brown
- CD Cedar
- WBK Weathered Black
- TT Two Tone

<sup>5</sup>Custom colors require upcharge

## Specifications

#### General

Traditional ornamental cast aluminum bollard with removable cap. The bollard includes 12 vertical slots and an internal white acrylic lens which creates uniform illumination with a high level of visual comfort. The bollard shall be UL listed in US and Canada.

#### Construction

The bollard is made of heavy wall 356 alloy cast aluminum with a 1" thick floor cast as an integral part of the bollard. The high tensile aluminum shaft shall be double circumferentially welded internally and externally to the bollard for added strength. The removable bollard cap is cast aluminum.

#### Quick-Release Mounting (Optional)

The bollard can include an optional quick release mount in lieu of anchor bolts, which allows for tool-less removal of the bollard for convenience or emergency access. The burial portion shall be installed in ground flush with grade, it shall be made of aluminum extrusion and shall have a wiring compartment, keyway and flexible aircraft cable connection system for securing the bollard to the ground. The removable bollard portion shall have a mated extension and anti-rotation key, along with a slot in the base for a lock to externally attach to the aircraft cable loop (LOCK BY OTHERS). The system comes with a quick release power connection for safety.

#### I FD's

The luminaire shall use high output, high brightness LED's, consisting of a two piece assembly complete with Chip on Board (COB) LED component and COB holder frame. The LED's and printed circuit boards shall be 100% recyclable; they shall also be protected from moisture and corrosion by a conformal coating of 1 to 3 mils. They shall not contain lead, mercury or any other hazardous substances and shall be RoHS compliant. The LED life rating data shall be determined in accordance with IESNA LM-80. The High Performance white LED's will have a life expectancy of approximately 100,000 hours with not less than 70% See next paae



800-621-3376 555 Lawrence Ave., Roselle, IL 60172 info@sternberglighting.com www.sternberglighting.com 8/20 STERNBERG LIGHTING. ALL RIGHTS RESERVED. PRINTED IN THE USA

## 6201LED OXFORD SERIES

of original brightness (lumen maintenance), rated at 25°C. The High Brightness, High Output LED's shall be 4000K (2700K, 3000K, 3500K or 5000K option) color temperature with a minimum of 70 CRI. Consult factory for custom color CCT. The luminaire shall have a minimum \_\_\_\_\_\_\_ (see table) delivered initial lumen rating when operated at steady state with an average ambient temperature of 25°C (77°F)

#### Optics

The luminaire shall be provided with an individual collimating type acrylic optic applied to the COB (Chip On Board) LED assembly. The luminaire shall provide a symmetric distribution with near perfect surface brightness and uniformity.

#### **Electronic Driver**

The LED driver shall be U.L. Recognized. It shall be securely mounted inside the bollard, for optimized performance and longevity. It shall be supplied with a quick-disconnect electrical connector on the power supply, providing easy power connections and fixture installation. It shall have overload, overheat and short circuit protection, and have a DC voltage output. constant current design, 50/60HZ. It shall be supplied with line-ground, line-neutral and neutral-ground electrical surge protection in accordance with IEEE/ANSI C62.41.2 guidelines. It shall be a high efficiency driver with a THD less than 20% and a high power factor greater than .9. It shall be dimming capable using a 0-10v signal, consult factory for more information.

#### Installation

Four 3/4" diameter, hot-dipped galvanized "L" type anchor bolts shall be provided with the bollard for anchorage, they shall be mounted in a 14" bolt circle. A door shall be provided for wirring and anchor bolt access. It shall be secured with tamper proof stainless steel hardware. Post will be provided with a grounding stud mounted on the base floor opposite the access door.

#### Photocell

The photocontrol shall be mounted on the bollard. The electronic button type photocontrol is instant on with a 5-10 second turn off, and shall turn on at 1.5 footcandles with a turn-off at 2-3 footcandles. Photocontrol is 120-277 volt and warranted for 6 years.


#### Warranty


Seven-year limited warranty. See product and finish warranty guide for details.


#### Finish

Refer to website for details.

### **Bollards**








PCD & CL2

Optional Photocell &

Double Chain Loops



GFI LPIUC Optional Duplex GFCI



**QR** Optional Quick Release Mount

## Performance

| LIGHT SOURCE | TS DELIVERED LUMENS | EFFICACY (LPW) | WATTAGE |
|--------------|---------------------|----------------|---------|
| 1L40TS-MDL07 | 590                 | 19.7           | 30      |
| 1L30TS-MDL07 | 575                 | 19.2           | 30      |
| 1L27TS-MDL07 | 520                 | 17.3           | 30      |



800-621-3376 555 Lawrence Ave., Roselle, IL 60172 info@sternberglighting.com www.sternberglighting.com 8/20 STERNBERG LIGHTING. ALL RIGHTS RESERVED. PRINTED IN THE USA.