

3500 CHARLESTON SERIES

SPECIFICATIONS

GENERAL

The ft tall* decorative post shall be aluminum, one-piece construction. The 11³/4" square cast aluminum octagonal base shall be constructed with a ____ inch diameter extruded aluminum shaft. The model shall be Sternberg Lighting #3500 or #3500R for candy cane poles. The pole shall be U.L. or E.T.L. listed in U.S. and Canada.

CONSTRUCTION

The base shall be designed with octagonal stepped base transitioning into a flared top section and be made of heavy wall, 356 alloy cast aluminum. It shall have a 3/4" thick floor cast as an integral part of the base. The bolt cover shall be made of cast aluminum. The shaft shall be double circumferentially welded internally and externally to the base for added strength.

The smooth tapered shaft shall be made of ASTM 6063 extruded aluminum and tempered to a T6 condition.

The **smooth straight shaft** shall be made of ASTM 6063 extruded aluminum and tempered to a T6 condition.


The straight fluted shaft shall be made of ASTM 6061 extruded aluminum and tempered to a T6 condition. It shall have a decorative fluted 3" O.D. tenon.

The **tapered fluted shaft** (not shown) shall be made of ASTM 6061 extruded aluminum and tempered to a T6 condition. It shall have a decorative fluted 3" O.D. tenon.


INSTALLATION

Four ¹/₂" diameter, hot-dipped galvanized "L" type anchor bolts shall be provided with the post for anchorage. A door shall be provided for wiring access. It shall be secured with tamper proof, stainless steel hardware. Post will be provided with a grounding stud mounted on the base floor opposite the access door.

Indicate the type of shaft needed (above)



*See installation template for exact door position.




AG ft (feet - above grade height). See diagram on reverse side




3500 CHARLESTON SERIES

POSTS / OPTIONS / POST CAPS



OPTIONS AVAILABLE

See Accessories Section for more options and information



POST CENTER CAPS (If Required)



BCC -Ball Center Cap



FCC -Finial Center Cap



SCC -Spiked Center Cap



TFCC -Tall Finial Center Cap



SSCC-Side Spiked Center Cap

