PRODUCT FEATURES

- $^{\bullet}\,$ "Head pivots 90° to direct the light exactly where it is needed "
- · Integrated push switch dimmer
- Perfect in a bedroom or wherever additional illumination is required
- The LED Driver is housed within the junction box. (L. 2.68" | W. 1.57" | H. 0.87")
- Head can pivot left and right 60°
- This fixture should not be used with a standard wall switch or dimmer.









To view all available finish options, please visit techlighting.com

LAMPING

ORDERING INFORMATION

SLTS678	COLOR TEMP	FINISH
	27 2700K	BZ BRONZE
		HAB HAND-RUBBED ANTIQUE BRASS
		B NIGHTSHADE BLACK
		PN POLISHED NICKEL


JOB NAME	
00D 10 111E	
NOTES	



PONTE 7 TASK SCONCE

SPECIFICATIONS

PRIMARY MATERIAL	Steel Or Brass			
SHADE MATERIAL				
NET WEIGHT	2.5 lbs			
HEIGHT	7.3in			
WIDTH	0.9in			
LENGTH	2.7in			
MIN. EXTENSION FROM WALL				
UP LIGHT / DOWN LIGHT / BOTH?				
WET LISTED				
DAMP LISTED				
DRY LISTED				
UP/DOWN				
HORIZONTAL/VERTICAL				
WALL/CEILING MOUNT				
GENERAL LISTING	ETL Listed			
ADA COMPLIANT				
INCLUDES				



LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP	
DELIVERED LUMENS		420			
WATTS		8			
MAX WATTAGE PER BULB		8W			
		120V Integrated 3-Step Touch Dir	mmer		
ССТ		2700K			
CRI		90 CRI			
LED LIFETIME					
L70		>50,000			
AVERAGE BULB HOURS					
FIELD SERVICEABLE LED					
LAMP BASE		Dedicated LED	Dedicated LED		
LAMP SHAPE		Dedicated LED	Dedicated LED		
LAMP INCLUDED?		True	True		
WARRANTY**		5 Years			

^{*} Dimming information available at <u>www.techlighting.com/Downloads#dimming</u>

T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6/JA8.	No		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.	N/A		

 $^{^{\}star}$ If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.



^{**} Visit techlighting.com for specific warranty limitations and details.