



## PA-M1WP

Order No.: 0179300

**Price upon request**

### PRODUCTINFOS

#### Wall module,

for local insertion of audio signals to PA matrix mixing amplifier PA-M224 or PA-M412.

- Intended application: volume control of 1 zone, local insertion of audio signals
- 2 x RCA jack for line signals
- Microphone connection via 3-pole XLR jack
- 14 V phantom power, to be activated as required
- Volume control
- Signal selector button with LED indication which allows a priority circuit of locally inserted audio signals (MIC or LINE) in the respective zone
- Connection to PA-M224 or PA-M412 and power supply via RJ45 jack and Cat. 5 network cable (copper, supplied w/o cable), cable length up to 200 m
- Matching flush-mounted housing ATT-300C is available at option

### TECHNICAL SPECIFICATIONS

**PA-M1WP**

Description	wall module
Type	remote control of 1 zone
Colour	white
Material	plastic
Suitable for	PA-M224, PA-M412
Power supply	via PA-M224, PA-M412
Dimensions	80 x 80 x 50 mm
Weight	90 g
Connections	1 x XLR (microphone), 1 x RCA L/R (line), 1 x RJ45
Other features	14 V phantom power
Packing unit	1