

About Dimmer Compatibility

The dimmers listed below were tested with the specified Magnitude LED drivers. We are constantly adding to our list of compatible dimmers.

This chart describes the lowest measured electrical output when using the dimmer/driver combination. Some dimmers have wider dimming range. Zero percentage (0%) means dim to off. One percent (1%) and five percent (5%) provide good dimming range. However, these percentages do not accurately describe the perception of the lamp, which is subjective to the individual viewer.

This compatibility list also takes into account other quality considerations such as flicker or pulsation. We do not recommend dimmers with these issues. In those cases where a dimmer is not compatible, we have suggested an alternate Magnitude product.

Minimum Dimming Percentage					
DIMMER TYPE	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0	
Lutron Caseta, Wireless	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
PD-6WCL (MLV)	to 0%	to 0%	to 0%	to 0%	
Lutron Maestro, Wireless	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
MRF2-6CL (MLV)	to 1%	to 1%	to 1%	to 1%	
Legrand Adorne ADWR700MMTU (MLV)	Not Recommended	Recommended Magnitude's M-Series Driver	Not Recommended	Recommended Magnitude's M-Series Driver	
Lutron Radio RA 2	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
RRD-6ND (MLV)	to 0%	to 0%	to 0%	to 0%	
Lutron Maestro	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
MA-600 (MLV)	to 0%	to 0%	to 0%	to 0%	
Legrand Adorne ADTP703TUW4 (MLV)	Approved	Approved	Approved	Approved	
Leviton Decore Smart DW6HD (MLV)	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
	to 0%	to 0%	to 0%	to 0%	
Lutron Nova T	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
NTLV-600 (MLV)	to 1%	to 1%	to 1%	to 1%	

Note: E-Series support MLV (forward-phase) dimming only

Page 1 hitlights.com



Minimum Dimming Percentage				
DIMMER TYPE	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0
Leviton illumatech IPM06 (MLV)	Approved	Approved	Not Recommended	Not Recommended
Lutron Ariadni AYLV-600P (MLV)	Recommended Magnitude's E-Series Driver	Approved Dims to 1%	Approved Dims 1%	Approved Dims
Lutron Diva DVLV-600P (MLV)	Approved Dims to 0%	Approved Dims to 1%	Not Recommended	Not Recommended
Lutron Diva DVCL-103P (MLV)	Approved Dims to 0%	Approved	Approved	Approved
Lutron Caseta, Wireless PD-10NXD (MLV)	Approved Dims to 1%	Approved Dims to 1%	Approved Dims 1%	Approved Dims
Lutron Maestro MA-PRO (MLV/ELV) MLV Result	Approved Dims to 1%	Approved	Approved	Approved
Lutron Radio RA2 RRD-PRO (MLV/ELV) MLV Result	Approved Dims to 1%	Approved	Approved	Approved
Lutron Caseta, Wireless PD-5NE (MLV/ELV) MLV Result	Approved Dims to 1%	Approved	Approved	Approved
LeGrand Adorne AADTP700RMTUM1 (MLV)	Approved	Approved	Not Recommended	Not Recommended
LeGrand Tru-Universa RH703PTUW (MLV Mode)	Approved	Approved	Not Recommended	Not Recommended
Lutron Diva DVCL-153P (MLV)	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 1%
Lutron Maestro + Motion Sensor MSCL-OP153MH	Approved Dims to 1%	Approved	Approved	Approved
Lutron Caseta Smart Home Plug-in PD-3PCL	Approved Dims to 1%	Approved Dims to 0%	Approved Dims to 0%	Approved Dims to 1%
Lutron Maestro MACL-153P	Approved Dims to 0%	Not Recommended	Not Recommended	Not Recommended
Lutron Maestro IR MIRLV-600P	Not Recommended	Not Recommended	Not Recommended	Not Recommended

Note: E-Series support MLV (forward-phase) dimming only



Minimum Dimming Percentage				
DIMMER TYPE	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0
Lutron Toggle	Approved Dims	Approved Dims	Approved Dims	Approved Dims
TGCL-153P	to 0%	to 0%	to 0%	to 0%
Lutron Toggle	Approved Dims	Approved Dims	Approved Dims	Approved Dims
TGCL-153P	to 0%	to 0%	to 0%	to 0%
Lutron Sunnata Touch	Approved Dims	Approved Dims	Approved Dims	Approved Dims
STCL-153P	to 0%	to 0%	to 0%	to 0%
Leviton Sureslide 6674	Approved	Approved	Approved	Approved
Leviton Toggle Slide TSM10-1LI	Approved	Approved	Approved	Approved
Leviton Decora Smart	Approved Dims	Approved Dims	Approved Dims	Approved Dims
DW1KD-1BZ	to 0%	to 0%	to 0%	to 0%
Leviton Decora Digital DDMX1-BLZ	Approved Dims	Approved Dims	Approved Dims	Approved Dims
	to 1%	to 1%	to 1%	to 1%
Leviton Decora Digital DDL06-1LZ	Not	Not	Not	Not
	Recommended	Recommended	Recommended	Recommended
Leviton Decora Slide	Approved Dims	Approved Dims	Approved Dims	Approved Dims
DSM10	to 1%	to 1%	to 1%	to 1%
Leviton Decora Slide	Approved Dims	Approved Dims	Approved Dims	Approved Dims
DSL06-1LZ	to 0%	to 0%	to 0%	to 0%
GE Z-wave plus	Approved Dims	Approved Dims	Approved Dims	Approved Dims
ZW3005	to 0%	to 0%	to 0%	to 0%
HALO Smart	Not	Not	Not	Not
HIWAC1BLE40AWH	Recommended	Recommended	Recommended	Recommended
WeMo WiFi	Approved Dims	Approved Dims	Approved Dims	Approved Dims
F7C059"	to 0%	to 0%	to 0%	to 0%
Insteon Smart	Not	Not	Not	Not
2477DH"	Recommended	Recommended	Recommended	Recommended
TP-Link Kasa Smart	Approved Dims	Approved Dims	Approved Dims	Approved Dims
HS220P3"	to 0%	to 0%	to 0%	to 1%

Note: E-Series support MLV (forward-phase) dimming only



Minimum Dimming Percentage					
DIMMER TYPE	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0	PWR-12V-060-67-D-K0	PWR-12V-040-67-D-K0	
Leviton Lumina RF	Approved Dims	Approved Dims	Approved Dims	Approved Dims	
DL1KD-1BZ	to 1%	to 1%	to 1%	to 1%	
Leviton Smart Sensor	Not	Not	Not	Not	
ODP10-I1W	Recommended	Recommended	Recommended	Recommended	

Note: E-Series support MLV (forward-phase) dimming only