# **LEDFIRE**







### **FEATURES**

- Fully compliant (AS/NZS 2293)
- Average power consumption <0.25W</li>
- Fast emergency switch-over (<0.5s) for high task areas
- Wireless mesh built on IEC62386-104 over Thread
- High Quality Lithium batteries (LiFePO<sub>4</sub>) and smart charger











CONTACT E: sales@evolt.com.au P: 1300 4EVOLT (438 658) F: +61 2 9502 1154 ektor.com.au







PRODUCT RANGE		Ľ	YNK
ORDER CODE	PRODUCT NUMBER	SKU	QTY
<b>EV-LEDFIRE-LK</b> Ektor Lynk Ledfire Professional Emergency Luminaire - w/wireless	9336462103937	10393	4

### **GENERAL FEATURES**

- Wireless meshing system
- Non-maintained operation
- Soft-start charger to reduce building load
- Lowest energy consumption (avg. <0.25W)</li>
- Selectable discharge rating for hazardous areas
- Fast emergency switch-over (<0.5s) for high-task areas

## **BUILT TO LAST**

- Long life electronics
- 10 Years Design Life 100,000 hours at max. ambient
- High Quality Lithium battery (LiFePO<sub>4</sub>)

# SUITABLE INSTALLATION TYPES (OUT OF THE BOX)

- IEC62386 over IEC62386-104
- Wireless monitoring
- Self test (AS2293/ IEC62034)

ACCESSORY RANGE	
ORDER CODE	DESCRIPTION
EV-LEDFIRE-PRO-RD	Ledfire Replacement dish
EV-1500MAH-6.4V-LIFEPO4	1500mAH 6.4V 2 Cell LiFePO <sub>4</sub> Battery
EV-CMS-2.4M-5PIN	CMS 5 Pin Plug Set, 2.4M
EV-WAGO-2.4M-F&P	WAGO Plug 5-P Blue 51110475, 2.4M
EV-WIELAND-2.4M-F&P	Wieland Plug GST18I5S B1 ZR1 S PB02, 2.4M
EV-WIREDBYCLICK-2.4M-F&P	Wire By Click 5-Pin Lead L1025/5, 2.4M
EV-CMS-2.4M-6PIN	CMS 6 Pin Plug Set, 2.4M

EMERGENCY PERFORMANCE						
HOUR	1	2	3	4	8	СВ
Classification	D50	D50	D20	D16	N/A	N/A

	L INFORMATION				
GENERAL	0401/ 5011-				
Voltage	240V~ 50Hz				
Ambient temp.	0 to 40°C				
Class	2				
IP rating	IP20				
Wiring	Flex and Plug				
Mounting type	Recessed				
Wireless	IEC62386-104 over Thread				
EMERGENCY					
Rated duration	90 / 120 min (1 / 3 / 4 / 8 hours, selectable)				
Rated lumens	260 lm (2 hr)				
Lamp power	2.7W				
Classification	D50				
BATTERY		CHARGE			
Туре	LiFePO <sub>4</sub>	Туре	Smart charge		
Voltage	6.4 V	Time	16 Hours		
Codes	01302	Operation	Adjustable		
CONSTRUCTION					
Inverter	PC V0, 850 glow wire	Dish	PC V2, 75	50 glow wire	
Cut out	Ø 70 mm - inner ring	Ø 75 - 130	mm - outer	ring	
COMPLIANCE					
Standards	AS/NZS 60598.2.22 AS/NZS 2293.3 IEC 60598-2-22	IEC 62386- IEC 62386- IEC 62386-	102	IEC 62034 CISPR 15	

**NOTE:** For more information on the chemical resistance of our polycarbonate or our compliance documentation, please see our website.

TOTAL POWER CONSUMPTION (TPC)				
MAX.	AVG.			
3 W	< 0.25 W			

**NOTE:** Average power consumption calculated with the assumption of four emergency events per year and that the battery charger is in standby at all other times (above typical usage).

SPACING TABLE (D50 - 0.2 LUX)				2005			
MOUNTING HEIGHT (M)							
2.1	2.4	2.7	3	3.3	3.6	4	4.5
18.0	18.7	19.4	20.1	20.7	21.2	21.8	22.5
5	6	7	8	9	10	15	20
23.2	24.2	24.9	25.4	25.7	25.9	23.7	15.2

ektor.com.au **E: sales@evolt.com.au** P:1300 4EVOLT (438 658)

