

29-31 Richland St. Kingsgrove. Sydney NSW 2208 Australia Phone: 02 9554 9600 | Fax: 02 9554 9433

enquiries@domuslighting.com.au | www.domuslighting.com.au

Installation Manual

EXPO-25-REC

Date: 08/2020

Variants		- I. N	C I I
Blk	Wht	— Item No.	Colour Iemp
20712	20713	EXPO-25-REC	TRIO
D /			

Description: LED Recessed Downlight

Thank you for purchasing your new EXPO-25-REC Wall Light, Please take the time to read and understand the instruction sheet below. Failure to do so may void warranty.

Specifications

oposition and the second and the sec							
Voltage:	240V AC	Lumen (±5%):	Warm White 3000K - 2200lm Neutral White 4000K - 2400lm White 5700K - 2600lm	Dimmable:	Yes		
Power:	25W	Beam Angle:	80°	Operating Temp:	-20°~45°C		
IP Rating:	IP44	CCT:	3000K - 4000K - 5700K (Switchable)				
CRI:	≥90	Lifespan:	50,000hrs				

For the product with Slide Switch of Color Selection, please select the light color (DL/CW/WW) before installation.




Step 1 Open a hole according to the cutout size of LED downlight




Step 2 Use screw-driver to open the driver terminal cover, feed the main AC wire L. N. in terminal block respectively, then fix the cover back.



Step 3 Connect the downlight with driver, hold back the spring clip then push the downlight into the hole.



Step 4 Connect the downlight with driver, hold back the spring clip then push the downlight into the hole



Note:

-The lamp must be installed by professional electrician

-Ensure the power supply is switched off before fitting this product

-Do not touch the lamp when in use

-Keep away from hot steam and corrosive gas