

## Festoon Lighting Installation Instructions



**Festoon Lighting can be dangerous if used incorrectly so please read carefully.**

- Before installing, inspect the lampholders to make sure there are no breaks to the seals.
- The power plug cap at the end of the festoon must always be on and turned tightly.
- **Avoid the lampholders with your fingers.** If you put your finger inside the lampholder you will get a shock.
- Do not hang above bodies of water.
- You must install the festoon lamps **facing down only**, not up, as the water will enter if facing up.
- Festoon application is strictly to be hung in the air or surface mounted to a roof or wall.
- When installing the festoon try not to make lengths longer than 6 meters for each drop. If longer than 6 meters use cable ties or hooks.
- When installing globes, ensure they are tightened as far as possible so that the seal is created.
- If a globe dies, the festoon will still run normally. However, it is crucial to leave the blown globe still intact in the lampholder as it will keep the water out.
- When installing the bulbs, make sure the festoon is **unplugged from the wall socket**.
- Do not cluster bulbs together in a bunch.
- **Do not exceed 1500 watts.**
- These festoons are able to use LED, Incandescent, CFL and halogen lamps.
- **24v low voltage model** – the LED 24v systems are more ideal for long term commercial or residential applications. They will run at less power and if something was to go wrong 24v is 0 risk of electrocution. When running the 24v system you can not connect multiple runs as the driver/transformer is only able to run the allocated wattage purchased. However, if you tell us before purchasing, we can increase the driver and lengths.
- Custom lengths are available, please email [customerservice@thelightingoutlet.com.au](mailto:customerservice@thelightingoutlet.com.au)

### **Technical Speciation's**

**IP44** ( Rated for indoor or outdoor )

**240v E27**

1.5 Meter Australian flex and plug included

**Warranty** – 2 years for the festoon string. **0 warranty for incandescent** globes, these are complimentary only. **LED** globes have a 2 year warranty, and **carbon filament** have a 1 year warranty.

**Warranty does not cover incorrect installation or placement.**

**Dimmable** – ( Only when using dimmable globes ) Check your wattage before purchasing the dimmer. Dimmers will have a certain load they can handle and you may be over the wattage.

**Read our blog on the website link below to learn the expert guide to festoon.**

[thelightingoutlet.com.au/blogs/news/festoon-lighting](http://thelightingoutlet.com.au/blogs/news/festoon-lighting)