

# CORE X11

Smartwatch User Manual



Designed by Neuclo

## **Thank you for choosing our product!**

To have a comprehensive understanding and using this device, to know all the features and simple operation method, please read this manual first.

The functions on the user manual may be a little different from the Neuclo Core X11 smartwatch, please contact our support team for any assistance you may need.

The additional features that we may add to the core x11 smartwatch may not be available on this manual, but you can also download our product's latest manuals from our website. Neuclo Technology Ltd reserves the right of final interpretation of our products user manuals.


Remark: The product supports waterproof with IP68 level, so it is available to wear it while you wash your hands, swim, take a shower, etc.

Package: 1x gift box, 1x user manual, 1x core x11 smartwatch, 1x product authenticity certificate.

Buttons instruction:


“Power” button: Long press the button 2 seconds for power on, and power on when charging. On function interface, long press - select power off, long press 2 seconds for power off.

Touch button: Touch for menu options, long touch to enter this function. Lighten up the screen in 1 second.





**Charging instruction:** the Neuclo core x11 smartwatch adopts magnetic force charging. Put the charging point connect to the back of the device charging pins, it will charge automatically. It usually takes 2 hours for a full charge and the device has a standby time of up to 30 days and up to 5 days whilst being used.



### **How to connect the core x11 smartwatch to your phone:**

Use Android/IOS system phone to scan "QR" code as below or download "GloryFit" APP on your phone and install it in the watch-Tooling.

It supports iOS 8.0 system and above, Android 4.4 and above, and also Bluetooth 4.0 connection.



As the Bluetooth protocol is different between for various mobile phone brands, sometimes the Bluetooth connection will be instable between the mobile phone and the core x11 smart watch. Please restart the Bluetooth, then try to connect again. Some settings on the phone need to be done for the data transmission to work smoothly.

Please ignore if your phone does not have those functions below:

1. Allow the app "GloryFit" work in the background.
2. Open all permissions for the app "GloryFit".
3. Permit the app "GloryFit" to get all the notifications.
4. Get the app "GloryFit" in to white list.

**Connection:** Get the device close to your phone, turn on your phone Bluetooth and GloryFit, fill in the personal data, a process will be prompted for some permissions to be enabled in the settings, tap all allows, at the bottom right corner Device – Add a new device – searching bracelet name X11 (XXX) and select. It will be automatically connected and when the connection is successful, a device and phone binding will be displayed. For some mobile phones, you need to turn on the GPS to search the Bluetooth name of the watch.

**Notifications of incoming calls setting:** Into GloryFit to enter the device -- Apps reminder -- enter the notification permission, select "on" -- enter the accessibility and select "on", back, turn on the call reminder, SMS reminder, enter the APP reminder, select the APP that needs to be notified of synchronous, such as Facebook, WhatsApp, select On. Note that message alerts are blocked when heart rate and blood pressure measurements are performed and when in multi-activity mode. Note that if the WeChat computer version is online at the same time, the phone will not receive a letter notification.



Steps

27432



5.2km

8299E

10:59





## **What if I don't receive the notifications?**

First of all, the notification function of the core x11 smartwatch is only to synchronize the notification function of the mobile phone, such as incoming email, Facebook, WeChat reminder. If your mobile phone has not received the notification, then the core x11 smartwatch push notification is not properly enabled. To fix this, go to the settings in the mobile phone and allow the notification function, find the corresponding APP to allow the notification to open.

- Disconnect: If you want to disconnect the connection, at Device interface, tap upper right corner setting click to unpair.
- Firmware upgrade: In the same interface, click firmware upgrade, if there is a new software available, click to update to the latest bracelet software.
- Weather: After connecting to the GloryFit app, the core x11 smartwatch will automatically synchronize to the local weather status.
- Pedometer: It displays the total steps in a day, saves data at 12 o'clock every night and resets to 0.

- Time and Languages: Both of them will automatically sync once connected to the phone App GloryFit.
- Distance: It shows the steps covered in a day, saves data at 12 o'clock every night, & resets to 0
- Calories: It shows the calories burnt during the day, saves data at 12 o'clock every night and resets to 0.
- Heart rate: Stop at the Heart Rate interface for 3 seconds and get the heart rate data by scanning the surface capillary of the skin by green light, switch to other menus to stop measuring. The normal heart rate is generally 60-90 bpm, while professional athletes will have less than 60bpm but when doing strenuous exercise it will reach up to 200 bpm.
- Sleep monitor: The device will turn on this function automatically from 6p.m to 8 a.m. every night. You can check the detailed data of sleep quality by connecting to the APP on the phone.
- Sports: Press the Touch key for 2 seconds to enter the multi-sport mode, select a mode, press the Touch key for 2 seconds to enter and stop. There is a rope skipping and a swimming mode in the multi-sport modes.

- Find phone: Function - find the phone, press the touch button for 2 seconds to enter/stop.
- Decline calls: Decline an Incoming call by long pressing the touch button for 2 seconds.
- Alarm: Multiple alarm clocks can be set up via APP on mobile phone.
- Brightness: Adjust the brightness you need by holding for 2 seconds to confirm.
- Restore Settings: Enter function - restore settings - long press touch button for 2 seconds and reset successfully.

## **Warranty**

1. If there are any quality problems caused by manufacturing, materials, design within one year (since the day of purchase, we will offer free warranty for main part. We will offer free warranty for battery and adapter within 6 months on the premises that the core x11 smartwatch has been used normally and correctly.
2. If the fault has been caused by careless use, we will not offer free warranty.

# CORE X11

Core X11 Smartwatch is designed by Neuclo, a British company with the registration number 11029408.

