Motion detector - Professional Line

sensIQ S

EVO black EAN 4007841 034979 Article number 034979







Function description

The evolution of perfection. The sensIQ S is just as perfect as its larger role model. For indoors and outdoors, ideal for building entrances, loading bays, for mounting heights of up to 5 m, quadruple sensor system for optimum surveillance over 3x100° coverage angle, 20 m reach (tangential), reach setting to the accuracy of a metre in 3 independent directions. Remote control and corner wall mount bracket included.

Technical specifications

Dimensions (L x W x H)	128 x 114 x 74 mm	LED lamps > 2 W < 8 W
With motion detector	Yes	LED lamps > 8 W
Manufacturer's Warranty	5 years	Capacitive load in µF
Settings via	Remote control, Potentiometers, Smart Remote	Power supply, detail
	Smart Remote	Technology, sensors
With remote control	Yes	Mounting height
Version	black	Mounting height max.
PU1, EAN	4007841034979	Optimum mounting height
Туре	Motion detectors	Detection angle
Application, place	Indoors, Outdoors	Angle of aperture
Application, room	multi-storey / underground car park, outdoors, warehouse, front door, all round the building, courtyard & driveway, Indoors	Sneak-by guard
		Capability of masking out individual segments
Colour	black	Electronic scalability
Colour, RAL	9005	Mechanical scalability
Includes corner wall mount	Yes	Reach, radial
Installation site	wall, corner	Reach, tangential

https://www.steinel.de

Subject to technical modifications

09.2023 Page 1 from 3

300 W 600 W 176 µF

500 VA max., 120 V

2,00 - 5,00 m 5,00 m 2 m 300 ° 180 ° Yes

Yes No Yes

 $r = 4 m (42 m^2)$ $r = 20 m (1047 m^2)$

passive infrared, Light sensor

Motion detector - Professional Line

sensIQ S

EVO black EAN 4007841 034979 Article number 034979



Technical specifications

Installation	Surface wiring, Wall, corner	
IP-rating	IP54	
Ambient temperature	-20 - 50 °C	
Material	Plastic	
Mains power supply	100 – 240 V / 50 – 60 Hz	
Switching output 1, resistive	2000 W	
Switching output 1, number of LEDs / fluorescent lamps	50 pcs.	
Fluorescent lamps, electronic ballast1500 W		
Fluorescent lamps, uncorrected	1000 VA	
Fluorescent lamps, series-corrected	1 700 VA	
Fluorescent lamps, parallel- corrected	1000 VA	
Switching output 1, low-voltage halogen lamps	1000 VA	
LED lamps < 2 W	100 W	

Switching zones	1360 switching zones
Functions	Normal / test mode, Manual ON / ON-OFF
Twilight setting	2 – 1000 lx
Time setting	5 s – 15 Min.
Basic light level function	No
Main light adjustable	No
Twilight setting TEACH	Yes
Constant-lighting control	No
Interconnection	Yes
Type of interconnection	Master/master
Interconnection via	Cable

Accessories

EAN 4007841 007638	Remote control RC9
EAN 4007841 608804	Corner wall mount sensIQ S
EAN 4007841 608835	Corner wall mount sensIQ S
EAN 4007841 009151	Remote control Smart Remote
EAN 4007841 608828	Corner wall mount sensIQ S


Motion detector - Professional Line

sensIQ S


EVO black EAN 4007841 034979 Article number 034979



Detection Zone




Dimension Drawing




Possible mounting height: 2,00 m – 5,00 m Orange: radial Black: tangential 3 scalable zones


Light without neutral conductor



Connection using two-circuit switch for manual and automatic operation



Light with neutral conductor



Connection of 4-fold push-button coupler to DALI2 APC

