## AirScape

## **2500-LL-D Whole House Fan**

2948 CFM, 345 W, 36-52 dBA, R9.6

Our most efficient model with our <u>patented</u> 20" fan ducted from an acoustical box with a motorized Lift-Lock door (R9.6). The unit fits 16" and 24" O/C framing. The included <u>Digital Touch Controller</u> controls 10 speeds allowing for harmonic and efficiency selection in your preference. This controller also includes a 12 hour timer and dims its indicator lights when left alone.





AirLab Specifications:			
Fan Speed	Power (Watts)	Air Flow CFM	Efficiency (CFM per W)
<mark>1</mark>	<mark>14.7</mark>	<mark>459</mark>	<mark>31.22</mark>
<mark>2</mark>	<mark>21</mark>	<mark>816</mark>	<mark>38.86</mark>
<mark>3</mark>	<mark>33</mark>	<mark>1153</mark>	<mark>34.94</mark>
<mark>4</mark>	<mark>51.7</mark>	<mark>1437</mark>	<mark>27.79</mark>
<mark>5</mark>	<mark>79.8</mark>	<mark>1724</mark>	<mark>21.6</mark>
<mark>6</mark>	<mark>117</mark>	<mark>2003</mark>	<mark>17.12</mark>
7	165.6	2297	13.87
8	224	2568	11.46
9	302	2813	9.31
10	345	2948	8.54
High Efficiency Range			

120VAC, 60Hz,Single Phase, 2.9 A Unit Weight = 120 lbs Links:

www.airscapefans.com 1.866.448.4187 AirScape your house!

How does a Whole House Fan work? The highest quality and quietest fans on the market today!

Easy Installation, how to DIY\_

Check out our sister company HVACQuick.com



