BACK

PROTOCOL.

HOW TO USE:	HOW TO VIEW:
 Record Video: 1. Press the On/Off button again to start recording. The blue light will blink 3 times and go off. The video will start to record and will automatically save every 5 minutes to the card. 2. To stop recording, press On/Off again. The light will turn on to steady blue. 	 Connect Spy Cube to the USB port of your computer or insert the memory card into a reader (not included). Alternatively, you can view on your TV using the included TV cable.
 Motion Activated Video: 1. Spy Cube is preset to record steadily. 2. To switch to motion-activated recording, press the Mode button for 3 seconds. 3. The indicator light will blink red and blue and Spy Cube will then only record when it detects movement. 4. Press the mode button again to switch back. Photo: Press the Mode button once to enter photo mode. The indicator light will show steady red. Press the On/Off button once to take a photo. The red LED will blink once to show the photo is taken. 	 RESET: 1. If you are having trouble with the camera, you have the option to reset. 2. With the camera in standby mode, take the reset pin and insert it into the reset hole. 3. The blue light will go off. Power the camera back on again to use.
 Night Vision: 1. Press and hold the On/Off button for 2 seconds and release. The indicator light will blink red twice. 2. To turn off night vision, press and hold the On/Off button for 2 seconds again. The indicator light will blink red three times. 	 WARNINGS: Research and understand the laws about recording other people. Make sure anyone you record understands that they are being recorded. Camera should not get wet.

PROTOCOL

Read through this entire instruction manual BEFORE using the Spy Cube. We're dedicated to bringing you welldesigned products that make living fun and easy. We stand behind all our products and warrant this to be free from defects in workmanship and materials.

COVER

Instruction Manual

HD SECURITY VIDEO CAMERA SPY CUBE[™]



For service claims or questions please consult our website ProtocolDesign.com.

PROTOCOL

	PARTS:		SET UP:	SET UP:
	1. On/Off	7. Charging Port	Charging the Spy Cube:	Setting The
	 Mode (Video/Picture) Night Vision Light 	8. Charging/TV Cable 9. Mount	 Plug the cord into the Spy Cube and the other end into a USB port. 	1. After insert leave it in s The camer
	 4. LED Indicator 5. Camera 	10.Clip 11.Reset Hole	The LED Indicator will blink red while charging. Charging time is 1-2 hours for 1 hour of power.	2. Connect th
	6. Memory Card Slot	12.Reset Pin	 3. The indicator light will go steady once fully charged. * Low Battery – the indicator will flash blue and red for 5 seconds 	 Open TIME The format
			and Spy Cube will shut down. Anything recorded up until that point will save to the memory card.	5. Example: 7 2019-01-0
			** You can use Spy Cube while charging.	6. Set the cu
	4.	6 1	Install the Memory Card (not included):	7. Videos will
	2		 Spy Cube records to a standard sized memory card which can be purchased at your local electronics retailer. 	Mounting Sp
			2. Push the memory card into the slot.	1. Included a
			If the memory card is not installed or if it is full, the indicator light will flash red and blue and Spy Cube will shut down.	2. Install the i (not includ
		*Pay attention to how much space is left on the card. Once the	3. Slide the c	
		card is full, Spy Cam will automatically start to delete the oldest photos/videos to make room for new.	4. Adjust to d	

Powering On & Off:

- 1. Press the On/Off button and hold for 2 seconds to turn on.
- 2. The indicator light will turn to steady blue. This is standby mode.
- 3. Press and hold the On/Off button for 6 seconds to turn off Spy Cube.
- * Spy Cube automatically turns off after 1 minute in standby mode.

PROTOCOL

PROTOCOL

e Time Stamp:

erting the memory card into the camera, turn it on and n standby for at least 10 seconds before turning off. nera will create a txt file called TIME.txt.

the camera to the computer and open the drive.

ME.txt in a text editor and format the file.

nat is YYYY-MM-DD-HH-MM-SS.

e: To set to midnight exactly on January 1, 2019 enter -01-00-00-00.

current time and save the file.

vill now show the timestamp.

Spy Cube (optional):

I are a mount and a clip.

e mount to a desired location using 2 screws uded).

clip onto the camera and clip to the mount.

desired viewing angle.

PROTOCOL