



XP10000HX

DUAL FUEL PORTABLE GENERATOR

10,000 STARTING WATTS • 8,000 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY





XP10000HX

DUAL FUEL PORTABLE GENERATOR

FEATURES

- Large Fuel Tank
- All Metal Construction
- Powerful OHV Engine
- All-Copper Windings
- Digital Command Center
- Fully-Loaded Power Panel
- Push Button Start
- Low Oil Sensor



CO ALERT TECHNOLOGY

OUTLETS



X4

120V 20A
GFCI Outlet



X1

120V 30A
Twist Lock



X1

120/240V 30A
Twist Lock



X1

120/240V 50A
Heavy Duty Outlet

SPECS

Watts (Gasoline)	10,000 (peak) • 8,000 (running)
Watts (Propane)	9,500 (peak) • 7,600 (running)
Engine	OHV 439cc
Amperage	66.67A / 33.33A
Voltage	120V / 240VAC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	10.4 hrs
Runtime (Propane) at 50% Load	8.6 hrs