



XP13000EH

DUAL FUEL PORTABLE GENERATOR

13,000 STARTING WATTS • 10,500 RUNNING WATTS






XP13000EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS



X2
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V
30A Twist
Lock



X1
120/240V
50A Heavy
Duty Outlet

SPECS

Watts (Gasoline)	13,000 (peak) • 10,500 (running)
Watts (Propane)	12,350 (peak) • 9,975 (running)
Engine	OHV 500cc
Amperage	87.50A / 43.75A
Voltage	120V / 240VAC & 12VDC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	8.5 hrs
Runtime (Propane) at 50% Load	6.5 hrs