



XP15000EH

DUAL FUEL PORTABLE GENERATOR

15,000 STARTING WATTS • 12,500 RUNNING WATTS






XP15000EH

DUAL FUEL PORTABLE GENERATOR

FEATURES



OUTLETS



X4
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock



X1
120/240V
30A Twist
Lock



X1
120/240V
50A Heavy
Duty Outlet

SPECS

Watts (Gasoline)	15,000 (peak) • 12,500 (running)
Watts (Propane)	14,250 (peak) • 11,400 (running)
Engine	713cc V-Twin
Amperage	104.00A / 52.00A
Voltage	120V / 240VAC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	9.03 hrs
Runtime (Propane) at 50% Load	8.58 hrs