



# XP5500E

## PORTABLE GAS GENERATOR

5,500 STARTING WATTS • 4,500 RUNNING WATTS





# XP5500E

PORTABLE GAS GENERATOR

## FEATURES



Large Fuel Tank

All Metal Construction

Powerful OHV Engine

No-Flat Tires


All-Copper Windings

Fully-Loaded Power Panel

Low Oil Shutoff

Idle Control

## OUTLETS



**X2**  
120V 20A  
GFCI Outlet



**X1**  
120/240V  
30A Twist  
Lock



**DOUBLE THE  
120V AMPERAGE**

## SPECS

<b>Watts</b>	5,500 (peak) • 4,500 (running)
<b>Engine</b>	OHV 224cc
<b>Amperage</b>	37.50A / 18.75A
<b>Voltage</b>	120V / 240VAC & 12VDC
<b>Frequency</b>	60 Hz
<b>Fuel Type</b>	Gasoline
<b>Runtime at 50% Load</b>	8.92 hrs
<b>Start Type</b>	Electric / Recoil