



XP9000iH

DUAL FUEL DIGITAL INVERTER

9,000 STARTING WATTS • 7,600 RUNNING WATTS



FEATURING CO ALERT TECHNOLOGY





XP9000iH

DUAL FUEL DIGITAL INVERTER


FEATURES

- Clean Power
- Remote Start
- Parallel Capability
- Easy to Transport
- Dual Fuel Technology
- Digital Control Center
- All Copper Windings
- Runs Quietly (68dBA)



CO ALERT TECHNOLOGY


OUTLETS



X4
120V 20A
GFCI Outlet



X1
120V 30A
Twist Lock
(Adapter)



X2
USB-A USB-C
Outlets



X1
120/240V
30A Twist Lock

SPECS

Watts (Gasoline)	9,000 (peak) • 7,600 (running)
Watts (Propane)	8,550 (peak) • 7,200 (running)
Engine	OHV 459cc
Amperage	71.26A
Voltage	120V / 240VAC
Fuel Type	Gasoline / Propane
Runtime (Gasoline) at 50% Load	11 hrs
Runtime (Propane) at 50% Load	9 hrs