

# TIBO




## **Sphere Range – User Manual**

# Contents

- Safety Information
- Introduction
- First time speaker setup
- Wi-Fi mode
- Solo mode and group mode
- Using the pre-set functions
- Bluetooth mode
- Line In mode
- Additional Information
- Troubleshooting
- Specifications

## • Safety Information


Do not share the power socket with another appliance.



Do not disassemble or attempt to repair the appliance on your own.



If you are not using the appliance, pull the power cord out of the mains socket.



Be careful of the power cord and maintain it as appropriate.

To ensure safety, do not twist the power cord, do not pull it out of the socket, do not compress it or stretch its length.



Do not use the appliance if the supply voltage is lower than 90V or higher than 240V.

If the supply voltage is lower than 90V, the appliance may not work and its lifetime may be affected. If the voltage is higher than 240V, the appliance may catch on fire or cause a fire.

AC 90-240V

Do not wash the appliance or use it in the bathroom, or it may cause potential injuries and other problems.



### **Installation location**

Leave sufficient space around the appliance of at least 5 cm from any wall/obstacle to ensure proper ventilation and prevent the appliance from overheating.

The following places are not suitable installation locations for the appliance:

- An unstable location
- A location near a heat source or in direct sunlight.
- In a wet or dusty environment

### **Warning**

To prevent suffering an electrical shock or another accident, do not operate the appliance in a rainy or humid environment.

### **Cleaning and maintenance**

Use a soft cloth or cotton dipped in a neutral solution for cleaning the surface of appliances. Do not use the type of cloth that you use for washing dishes or aggressive chemical agents.

## **Storm**

If the appliance is not working properly during a storm, please disconnect the plug from the power socket and reinsert it after a minute.

## **Do not drop small items or a liquid into the appliance**

In the event that you find small items or a liquid inside the appliance, you see smoke or smell an odour, immediately disconnect the appliance from the power grid. Send the appliance to an authorised service centre.

## **Repacking the appliance**

When sending the appliance by a transport company, use the original packaging to prevent its damage during transport.

- Introduction

Thank you for purchasing the TIBO Sphere speaker. We hope that your experience with the Sphere will be enjoyable for many years to come.

The Sphere range is a family of wireless smart speaker systems. They are able to connect to one another utilising the latest in exclusive Smart Audio software to deliver a high quality, crisp sound. Designed with motion in mind, you can play whatever and wherever you feel.

Wirelessly connect your mobile phone, tablet or other Wi-Fi/Bluetooth device. The rechargeable lithium ion batteries allow you to listen to music for up to 12 hours on full charge. Portable, powerful, quick and easy to set up. The specialised iOS and Android app offers a simple yet great experience for your music streaming and multiroom set up.

The Spotify software is subject to third party licenses found here:  
<https://developer.spotify.com/esdk-third-party-licenses/>



- First time speaker setup

### **In the box**

- Sphere speaker
- UK standard plug
- EU standard plug
- Quick start guide
- Setup warning

## Front panel layout



1. Pre-set functions: Toggle between pre-sets 1-5
2. Power light: Flashing red light when charging
3. Mode light: Red light – Wi-Fi mode, Blue light – Bluetooth mode, Green light – Line in mode
4. Group function: Press to group Sphere with other Smart Audio products
5. Play/Pause/Pair: Short press - Play/Pause, Long press - Bluetooth pairing mode
6. Power/Mode: Long press - Turn on/Standby  
Short press - Toggle between Wi-Fi, Bluetooth and Line in modes
7. Volume up/Skip track forwards: Long press - Volume up, Short press - Skip track forwards
8. Volume down/Skip track backwards: Long press - Volume down, Short press - Skip track backwards



## Rear panel layout



1. LAN Port: Direct connection for the Sphere to a router
2. USB Port: For charging your phone or tablet
3. 3.5mm Line In Port: For playing music directly from your phone/tablet
4. WPS Button: For connecting to the internet in Wi-Fi mode
5. Mains Port: For charging the Sphere

## Initial setup steps

1. Before using this product for the first time, please connect the power cable and leave to charge for 30 minutes.
2. Then turn on the Sphere speaker by pressing and holding the power button until the mode light turns on.
3. The Sphere will respond by saying “Power on, powering up for the first time, please wait.”
4. Do not do anything until the Sphere has finished booting up. The Sphere will say “Ready for app setup” when boot up is complete.

## App download

The TIBO app helps you get setup for the first time, and helps get the most out of your speaker’s functions. The app is compatible with iOS and Android smartphones, and can be downloaded for free on Google Play or in the App Store.




With the TIBO app you can:

- Browse and connect to over 15000 internet radio stations
- Select a sound source
- Manage Multi Mode groups
- Set up, modify, and play your pre-sets
- Check what song or other media is currently playing
- Adjust individual and multi-room volume settings
- Rename your speaker
- Adjust panning
- Add more speakers

- Wi-Fi mode

## Wi-Fi mode setup

1. Turn on the Sphere by pressing and holding the power button until the mode light turns on. Then short press the mode button until the speaker replies with “Wi-Fi mode.” (The mode light will turn red)
2. Open the TIBO app on your Android or iOS device and follow the instructions on screen.
3. Once opened, if your TIBO app has no devices connected to it, the screen should look like this. (See below) Click on ‘Wi-Fi Setup Wizard’ at the bottom of the page.



4. Make sure you're connected to 2.4G Wi-Fi as TIBO Smart Audio products are only compatible with 2.4G Wi-Fi. Then press 'Next'.




5. Find your Wi-Fi network, type in your password and then press 'Next'.



6. Short press the WPS button on the rear of the Sphere. The speaker will respond by saying "Searching for Wi-Fi connection." Then press 'Next'




7. Then wait for the Sphere to connect to your Wi-Fi. When connected, the Sphere will respond by saying “Wi-Fi connected. Then press ‘Next.’”



8. You can now name your Sphere speaker within the app. Either select from the list of pre-set options or click on custom to set your own name. Then press ‘Finish.’




9. Your Sphere will now appear on your 'Device List' within the app. To add more devices, press the 'cross' icon in the top right of the screen.



## Playing music via Spotify

1. Play some music in Spotify.
2. Click on 'Devices Available' at the bottom of the screen on Spotify.



3. Find your Sphere on the list and connect.





## Playing Internet Radio and My Music




1. Swipe left and right to navigate between each page of the app. Click on 'My Music' to play music from your device or click 'TuneIn' to search for thousands of internet radio station.




- Solo and Multi mode

1. In order to use this setting, you will need a minimum of 2 TIBO Smart Audio products. These can be any TIBO Smart Audio products. Press the cross + icon in the top right corner to add more devices to your Wi-Fi.



2. To group speakers together, simply press and hold one of the speakers within your 'Device List' and drag it on top of another speaker.




3. When grouped together, the Sphere will respond by saying "group mode." There will also be a white line on the app to show the connection of grouped speakers. You can

group up to a maximum of 16 Smart Audio products together.

- Using the pre-set functions


1. On the main menu of the TIBO app, click on TuneIn and search for the radio station that you'd like to save as a pre-set.



2. Next to all the radio stations you will see a speaker icon on the right of the screen.



3. Click on the speaker icon to open the pre-set content. Then click on any of the pre-sets 1-5 to save a radio station as a pre-set. The Sphere will respond by saying “pre-set saved.”



4. Press the corresponding number button on the Sphere to recall the pre-set.

- Bluetooth mode


1. Hold the power/mode button to turn on. If performed correctly, speaker will respond by saying "Power on." The speaker will then tell you what mode is currently activated. E.g. Wi-Fi mode.
2. Short press the mode button until the speaker responds saying "Bluetooth mode." The mode light will also turn blue.
3. Enable the Bluetooth setting on your source and your source will then automatically search for nearby Bluetooth devices.
4. When 'TIBO Sphere' appears on your list of 'available devices' on your source, click to pair your source with the Sphere. When connected, the speaker will respond saying "Bluetooth connected."
5. You can now play music to the Sphere via your device.

- **Line In mode**

1. Whilst the Sphere is turned off, connect a 3.5mm jack cable to the 'Line in' port at the rear of the speaker and the other end of the cable to your source. This is to avoid speaker pop when the speaker is turned on.
2. Hold the power/mode button to turn on. If performed correctly, speaker will respond by saying "Power on." The speaker will then tell you what mode is currently activated. E.g. Wi-Fi mode.
3. Short press the mode button until the speaker responds saying "Line In mode." The mode light will also turn green.
4. You can now play music to the Sphere via your source.

- Additional Information

1. **Software updates:** Every so often you may have the opportunity to update the software. This is due to new functions and improved performance. A red 'update' box will appear next to the 'settings' icon on the TIBO app when there are updates available.



2. **Factory reset:** Pressing the WPS button will make the Sphere search for a Wi-Fi connection. However if you HOLD the WPS for 5 seconds, the Sphere will restore itself to factory settings. The Sphere will respond by saying "restore to factory settings."
3. **Battery life:** The Sphere will last up to 12 hours when fully charged. When the battery percentage is 10% or lower, the Sphere will respond saying "Battery low" every so often.



## • Troubleshooting

<b>Problem</b>	<b>Possible Cause</b>
No power	- The battery for the Sphere needs charging.
No sound	- The speakers are disconnected. - Volume control is at lowest level. - The 3.5 mm jack is not inserted properly.
Suddenly no sound during operation	- Speakers may have been disconnected from Wi-Fi/Bluetooth. - The product may have entered overheat protection mode. - 3.5mm jack disconnected
Bad sound/sound distorted	- Audio source problem. - Bad or incorrect speaker connections.
Product dropping in and out of Wi-Fi	- Wi-Fi speed - Product too far away from router
Cannot connect to router	- Ensure router is dual band, as TIBO products only connect with 2.4GHz and NOT 5GHz
Product dropping in and out of Bluetooth	- Source is too far away from speaker - Bad Bluetooth signal from source

## • Specifications

Product name	Sphere 2
Power supply	Battery – 2200mAh x 4pcs
Sensitivity	-16dB
Frequency response	60Hz – 20kHz
Impedance	8 ohms
Bluetooth range	10 meters
Dimensions	256 x 125 x 155mm
Weight	2.45kg
Sound resolution	24 bit/192kHz

Product name	Sphere 4
Power supply	Battery – 2200mAh x 4pcs
Sensitivity	-16dB
Frequency response	50Hz – 20kHz
Impedance	4 ohms
Bluetooth range	10 meters
Dimensions	269 x 135 x 180mm
Weight	3.2kg
Sound resolution	24 bit/192kHz

Product name	Sphere 6
Power supply	Battery – 2200mAh x 4pcs
Sensitivity	-16dB
Frequency response	45Hz – 20kHz
Impedance	8 ohms
Bluetooth range	10 meters
Dimensions	309 x 170 x 210mm
Weight	4.2kg
Sound resolution	24 bit/192kHz

The Bluetooth® word mark and logos are registered trademarks owed by Bluetooth SIG Inc. and any use of such marks by Andersson is under license. Other trademarks and trade names are those of their respective owners.