



Q-Cover™

Revealing a better way

Junction Box Cover, Device Adapter

Part Numbers

Q-Cover QC100
Q-Cover with Access Hole QC101


Application:

The Q-Cover is used exclusively with our Q-Hub to create a 19.5 cubic inch junction box (Q-Box). Also used to connect 3rd party luminaires and other devices to our Q-Hub. Includes mounting holes for 3.5" and 3" devices for a #8 coarse thread screw.

Features:

- No assembly screws
- FicientLock™ system
- Compatible with QH1000(S), QBJA
- 3rd party device mounting holes

FicientLock™ Technology



Q-Cover
#QC100




Q-Hub
#QH1000S



Q-Box
#QHC1100

"Twist, Lock, and It's Water Tight!"



Material Non-metallic, high performance polycarbonate

Compatibility Compatible with Q-Hub QH1000(S) & Universal Junction Box Adapter QJBA

Device Mounting* QC100 and QC101 have predrilled holes for 3" and 3.5" third party devices and light fixtures

*When mounting devices to the Q-Cover do not penetrate the back of the cover with the screws. A plastite thread cutting screw is recommended and are available from Energy Efficient

Dimensions 1/4" H x 4 1/2" W

Packaging QC100/QC101: 15 per box; Box Size: 9.38" x 5.63" x 4.56"; Weight: 3 lbs



Recyclable materials



ETL listed for wet locations



Indoor/
outdoor use



USA Made